名称：Z03说明书
材质：铜版纸
尺寸：120*60mm
索订：烫镀钉
注：成品仅有黑色边框

Fosi Audio

ZD3 User Manual

Introduction

Thank you for purchasing the ZD3 Balanced Stereo DAC.

The ZD3 is a HiFi grade balanced stereo DAC, meticulously developed by Fosi Audio after thoroughly understanding user needs. It features an ESS ES9038Q2M DAC chip, supporting PCM decoding up to 384kHz/32bit, the proprietary Jitter eliminate circuit and the balanced analog circuit design. The ZD3 also features high-quality capacitors and low-drift capacitors ensure minimal signal processing errors and maintain signal purity. Equipped with USB, coaxial, and optical connectivity options, we are confident it will take you on a superb journey into HiFi music. Thank you again for your support. Fosi Audio is committed to providing you with more high-quality products to keep your enjoyment sound quality.

1. Input Mode
2. Current Sampling Rate
3. PCM/DSD Bitpattern Audio Decoding Format Indicator
4. Volume Level Mode

1. Bypass Switch
2. Main Volume Knob/Power Switch/Input Mode Selector
3. RJ9 Right Channel Output (3ft standard)
4. RJ9 Left Channel Output (3ft standard)
5. RCA Right Channel Output
6. RCA Left Channel Output
7. 12V Trigger IN (3.5mm Port)
8. 12V Trigger Out (3.5mm Port)
9. Coaxial Input
10. HDMI (ARC) Input
11. Optical Input
12. USB Input
13. Bluetooth Antenna
14. 12V DC Power Connection
15. OLED Display
16. USB Complying Port

Specifications

Chipset	ESS9038Q2M(ES9038Q2M+ES9038Q2M)*2
Maximum Sampling Rate	USB: PCM 384kHz/32bit HDMI: PCM 192kHz/24bit Optical/Coaxial: PCM 96kHz/24bit
Output Level	RCA 2Vrms RCA: 2.5Vrms
Input	USB, HDMI (ARC), Coaxial, Optical, Bluetooth,
Output	RCA, RCA
SNR	120dB
THD+N	<0.0005%
Dynamic Range	120dB
Noise Floor	<2uV
Frequency Response	20Hz~20kHz (±0.1dB)
Bluetooth Version	Bluetooth 5.0
Bluetooth Transmission Audio Format	aptX, SBC, aptX, aptX HD
Input Voltage and Current	DC 12V/1.5A
USB Compatible Devices	Windows 7, 8, 8.1, 10, 11 (Driver-free support for most mainstream operating systems for details: Mac OS X, Linux (No driver required))

Package Contents

Operation Guide

Important note:

1.Do not power on the device until all connections have been completed. 2.Before plugging music, ensure the volume is set to a low level to avoid potential damage to the speakers or impacting your hearing with sudden loud sounds.

Power On/Off Operations

1. Short press the main volume knob of the ZD3 to power it on. The screen will illuminate, and the device will enter the last used input mode.
2. Press the ZD3 or its remote once to mute the volume; the volume will gradually decrease to zero. Press again to unmute, then go up to the previous volume.
3. Long press the main volume knob for approximately 3seconds to power off the device.

Volume Settings

1. Mute/Unmute: Press the "🔇" button on the remote control to mute the ZD3. When muted, a mute icon will appear on the corner of the screen. Press again to unmute.

2. Volume Adjustment: Use the remote control buttons to the "+" and "-" buttons or the remote control to adjust the volume of the ZD3.

Note: When using the Bypass mode, the ZD3 functions solely as a DAC with the volume fixed at 0 dB, and the volume cannot be adjusted.

Bypass Mode

1. When Bypass mode is activated, the ZD3 enters a pure DAC mode. In this configuration, the ZD3 functions exclusively as a digital to analog converter, bypassing all other processing functions. Ensure that the amplifier or active speakers are turned off before connecting to prevent damage to the equipment.

2. When Bypass mode is deactivated, the ZD3 switches to DAC+ preamp mode, allowing you to adjust the volume using the volume knob.

Connecting Input/Output Sources

1. Connect to a power amplifier or a pair of active speakers. 2. Connect to a digital audio source such as a computer, smartphone, or voice speaker. Ensure that the amplifier or active speakers are turned off before connecting to prevent damage to the equipment.

Bluetooth Input Mode

1. Press the main volume knob short to switch to Bluetooth input mode, or press the "Source" button on the remote control. The screen will display "PAIRING".

2. On your phone, computer, or other devices, open the Bluetooth settings and search for "FOSI Audio ZD3" to pair. The screen will show pairing successfully, the screen will display "CONNECTED".

3. Double-click the main volume knob to clear the Bluetooth pairing history and enter pairing mode.

Optical Input Mode

1. Connect one end of the optical cable to the ZD3 and the other end to the output device.
2. Press the main volume knob to switch to optical input mode or press the "OPT" button on the remote control. The name of the mode will then appear on the screen.

Coaxial Input Mode

1. Connect one end of the coaxial cable to the ZD3 and the other end to the output device.
2. Press the main volume knob to switch to coaxial input mode or press the "COAX" button on the remote control. The name of the mode will then appear on the screen.

HDMI (ARC) Input Mode

1. Connect one end of the HDMI cable to the ZD3 and the other end to the output device.
2. Short press the main volume knob to switch to HDMI input mode, or press the "HDMI" button on the remote control. The name of the mode will then appear in the top right corner of the screen.

3. The ZD3 features HDMI-ECT functionality, which allows for synchronized volume control. When connected, both the output device and the ZD3 are in HDMI mode.

Note: Synchronized power control can only be initiated by the device connected to the ZD3 cannot control the power of the output device simultaneously.

USB Input Mode

1. Connect one end of the included USB cable to the ZD3 and the other end to your computer.
2. Short press the main volume knob to switch to USB input mode, or press the "USB" button on the remote control. The name of the mode will appear in the top right corner of the screen.

Important Note:

1. How to Use ZD3 as a USB DAC for Your Computer?
[Windows]
ZD3 supports plug-and-play on Windows 8/10/11 systems without the need for additional drivers.
Use the included cable to USB cable to connect the ZD3 to your computer.
[Video] "Fosi Audio ZD3" as the audio output on your computer.
[Mac/iOS]
The Macbook also supports plug-and-play and does not require any drivers. Simply connect the ZD3 to your Macbook and select the Fosi Audio ZD3 as the output device.

2. When using the ZD3 under the Windows system, drivers are required to ensure optimal performance.
1.The computer's operating system is Windows 7 or older versions.
2.Playing DSD music files.
3.Using the ASIO driver to bypass the system with the resulting Mixer plugin to play DSD music, you do not need to install additional drivers.
4.Playing PCM 768kHz music files.
5.Using the ASIO driver to bypass the system.
Note: Windows may not support volume control in exclusive USB audio access mode.

12V TRIGGER

The ZD3 is equipped with bidirectional 12V TRIGGER input/output interfaces. When connected to a 12V trigger-compatible amplifier, it enables alternating the mute/unmute function of the amplifier.

The upstream device connected to Trigger IN, such as Mode DT-plays can control the power-on/standby mode of the ZD3.

The ZD3 can control the power-on and standby mode of the downstream device connected to Trigger OUT.

Turning Off the Display

You can turn off the display by lightly pressing the "Display" button on the remote control. Lightly press again to turn the display back on.

Note: The remote control requires two AAA batteries, which are not included in the package.

Frequently Asked Questions

1. The system is set up, but there is no sound?
● Ensure ● check if the display on the ZD3 front panel is lit.
● Check if the volume is set too low. Gradually increase the volume to an appropriate level.
● If using Bluetooth, ensure the device is paired.
● Audio cable not properly connected or faulty ● recheck the connections.

2. USB not recognized?
● Try a different USB port or faulty contact ● replace the USB cable.
● Computer malfunction ● check the computer or connect using a different computer.
● Insufficient power ● connect to a powered USB port.

Official Website: www.fosiaudio.com
Amazon Store: www.amazon.com/fosiaudio
Facebook Page: www.facebook.com/fosiaudioglobal
Youtube Channel: www.youtube.com/@fosiaudio
Official Forum: community.fosiaudio.com
Whatsapp: +86 137 9461 2254
Fosi Audio Service and Technical Support Email:
support@fosiaudio.com

Scan for more

Warranty and Maintenance

Fosi Audio pledges to give a 24-month limited warranty and support from the date of purchase. If you encounter any product-related issues, please contact our support team at **support@fosiaudio.com**.

About Us

Fosi Audio designs and builds innovative audio products with all our passion and expertise. We aim to bring you the ultimate sound quality, convenient connectivity, and useful features we value most. Our quality journey, We recently hope you can get as much enjoyment from our products as we've put into creating them.

Official Website: www.fosiaudio.com
Amazon Store: www.amazon.com/fosiaudio
Facebook Page: www.facebook.com/fosiaudioglobal
Youtube Channel: www.youtube.com/@fosiaudio
Official Forum: community.fosiaudio.com
Whatsapp: +86 137 9461 2254
Fosi Audio Service and Technical Support Email:
support@fosiaudio.com

Scan for more

产品简介

感谢您购买ZD3平衡立体声解码器。

ZD3是Fosi Audio经深度理解产品需求后，精心研发的一款HiFi级平衡立体声解码器，采用ESS ES9038Q2M芯片，支持PCM解码至384kHz/32bit，具有专有抖动消除电路和平衡模拟电路设计。ZD3还配备了高品质电容器和低漂移电容器，确保信号处理误差最小化，保持信号纯净。通过USB、同轴和光纤接口，我们相信它将为您带来一段卓越的HiFi音乐之旅。再次感谢您的支持，Fosi Audio将继续为您提供高品质的音频产品，以保持您的音质享受。

1. 输入模式
2. 当前采样率
3. PCM/DSD比特流音频解码格式指示器
4. 音量电平模式

1. 旁路开关
2. 主音量旋钮/开关机/输入模式切换
3. 右声道输出（3英尺）
4. 左声道输出（3英尺）
5. RCA右声道输出（模拟）
6. RCA左声道输出（模拟）
7. 12V Trigger IN (3.5mm 接口)
8. 12V Trigger Out (3.5mm 接口)
9. 同轴输入
10. HDMI (ARC)输入
11. 光纤输入
12. USB输入
13. 蓝牙天线
14. 12V DC电源接口
15. OLED显示屏
16. USB合规端口

规格参数

芯片组	ESS9038Q2M(ES9038Q2M+ES9038Q2M)*2
最高采样率	USB: PCM 384kHz/32bit HDMI: PCM 192kHz/24bit 光纤/同轴: PCM 96kHz/24bit
输出电平	RCA: 2Vrms RCA: 2.5Vrms
输入方式	USB, HDMI (ARC), 同轴, 光纤, 蓝牙
输出方式	RCA, RCA
信噪比	120dB
失真度	<0.0005%
动态范围	120dB
底噪	<2uV
频响特征	20Hz~20kHz (±0.1dB)
蓝牙版本	5.0
蓝牙音频传输格式	SBC, AAC, aptX, aptX HD
输入电压电流	DC 12V/1.5A
USB兼容设备	Windows 7, 8, 8.1, 10, 11 (对大多数主流操作系统免驱动; 详情请访问官网查询: Mac OS X, Linux (无需驱动))

包装清单

使用说明

注意：
1.在所有连接完成之前请勿开机。
2.在播放音乐前，请确认音量处于较低水平，否则突然过大的声音可能会导致扬声器损坏或对您的听力造成伤害。

开关机操作
1. 短按一下ZD3主音量旋钮可开机，此时音量将显示"Fosi Audio"字样，屏幕将点亮，并进入上次使用的输入模式。
2. 单击ZD3或遥控器上的"🔇"按钮可静音，音量将逐渐降低至零。再次单击可取消静音，音量将恢复至之前设置的音量。
3. 长按主音量旋钮约3秒钟可关机。

音量设置
1. 静音/取消静音：按遥控器上的"🔇"按钮可静音ZD3。静音状态下，屏幕角落会显示静音图标。再次按下可取消静音。

2. 音量调节：使用遥控器按钮"+"和"-"按钮或遥控器调节ZD3的音量。

注意：使用旁路模式时，ZD3仅作为DAC运行，音量固定为0分贝，无法调节音量。

旁路模式

1. 启用旁路模式后，ZD3进入纯DAC模式。在此配置下，ZD3专门以高质量数字信号转换为模拟信号，绕过其他所有处理功能。确保放大器或有源音箱处于关闭状态，以防设备损坏。

2. 关闭旁路模式后，ZD3切换至DAC+前置放大器模式，可通过音量旋钮调节音量。

连接输入/输出源

1. 连接功率放大器或有源音箱。
2. 连接数字音频源，如电脑、智能音箱。连接前请确保放大器或有源音箱处于关闭状态，以防设备损坏。

蓝牙输入模式

1. 长按主音量旋钮，切换至蓝牙输入模式，或按遥控器上的"Source"键。此时屏幕上方将显示"PAIRING"。

2. 在您的手机、电脑等设备上打开蓝牙设置界面，搜索并选择"FOSI Audio ZD3"进行配对。配对成功后，屏幕将显示"CONNECTED"。

3. 长按主音量旋钮可清除蓝牙配对记录，进入配对模式。

光纤输入模式

1. 将光纤线一端连接ZD3，另一端连接输出设备。
2. 长按主音量旋钮，切换至光纤输入模式，或按遥控器上的"OPT"键。此时屏幕上方将显示该模式名称。

同轴输入模式

1. 将同轴线一端连接ZD3，另一端连接输出设备。
2. 长按主音量旋钮，切换至同轴输入模式，或按遥控器上的"COAX"键。此时屏幕上方将显示该模式名称。

HDMI (ARC)输入模式

1. 将HDMI线一端连接ZD3，另一端连接输出设备。
2. 短按主音量旋钮，切换至HDMI输入模式，或按遥控器上的"HDMI"键。此时屏幕上方将显示该模式名称。

3. ZD3具有HDMI-ECT功能，实现音量同步控制。连接时，ZD3和输出设备均处于HDMI模式。

注意：请勿将未通过连接线与ZD3连接的设备用于控制ZD3。否则可能导致输出设备失效。

USB输入模式

1. 将附带的USB线一端连接ZD3，另一端连接电脑。
2. 短按主音量旋钮，切换至USB输入模式，或按遥控器上的"USB"键。此时屏幕上方将显示该模式名称。

重要提示：
1. 如何将ZD3作为电脑的USB解码器？
[Windows]
ZD3支持Windows 8/10/11系统的插拔式免驱功能，无需安装驱动程序。
使用附带的USB线连接ZD3与电脑。
[视频] 将"Fosi Audio ZD3"作为电脑的音频输出。
[Mac/iOS]
Macbook系统原生支持插拔式免驱功能，无需安装驱动程序。
连接ZD3与Macbook后，在输出设备中选择"Fosi Audio ZD3"即可使用。

2. 在Windows系统下使用ZD3时，需安装驱动程序以确保最佳性能。
1.电脑操作系统为Windows 7及更早版本。
2.播放DSD音频文件。
3.使用ASIO驱动程序绕过系统，并通过Mixer插件播放DSD音频时，无需额外安装驱动程序。
4.播放PCM 768kHz音频文件。
5.使用ASIO驱动程序绕过系统。
注意：Windows系统可能不支持独占模式下的音量控制。

产品保修

产品质量问题，我方提供两年质保服务。用户可以在两年内享受免费维修或更换服务。超出质保期后，将提供有偿维修服务。我们将尽力提供最优惠的价格。

有关保修"三包"规定的解释：

1.一般三包规定解释：在经销商手中或客户收到产品后7天内，如出现质量问题，可选择退换货。

2.质保期内的维修服务：在质保期内，若出现质量问题，我们将提供免费维修服务。

3.超出质保期的维修服务：超出质保期后，我们仍提供维修服务，但需收取维修费用。

4.人为损坏及保修期：人为损坏不在保修范围内。保修期从产品发货日期开始计算。

5.产品保修期限：产品保修期为一年。

6.客户责任：客户需妥善保管产品发票，以证明产品的购买日期。

关于我们

ZD3采用先进的一体式平面电路设计，以实现最佳性能。采用高品质电容器，以确保信号纯度。此外，还采用低漂移电容器，以减少信号处理误差，保持信号纯净。通过USB、同轴和光纤接口，我们相信这款产品将为您带来一段卓越的HiFi音乐之旅。再次感谢您的支持，Fosi Audio将继续为您提供高品质的音频产品，以保持您的音质享受。

官网：https://www.fosiaudio.com

客服邮箱：FOSI AUDIO官方服务邮箱 fosi.zol.com/index/1251218.html

QQ群：768575133

售后邮箱：support@fosiaudio.com

Scan for more

产品结构

1. 旁路开关
2. 主音量/开关机/输入模式切换
3. 右声道输出（3英尺）
4. 左声道输出（3英尺）
5. 12V Trigger IN (3.5mm 接口)
6. 12V Trigger Out (3.5mm 接口)
7. 同轴输入
8. 光纤输入
9. 蓝牙天线
10. 12V DC 电源接口
11. OLED 显示屏
12. USB合规端口
13. RCA 左声道输出

产品参数

型号	Fosi Audio
尺寸	120*60mm
颜色	黑色
材质	烫镀钉
重量	0.2kg
产地	中国

产品保修

保修期	一年
保修范围	产品质量问题
保修方式	免费维修/更换
保修期起始	发货日期
保修期内责任	提供免费维修或更换服务
保修期外责任	提供有偿维修服务
客户责任	保管发票以证明购买日期

操作指南

注意：
1. 在所有连接完成之前请勿开机。
2. 在播放音乐前，请确认音量处于较低水平，否则突然过大的声音可能会导致扬声器损坏或对您的听力造成伤害。

关闭操作
1. 短按ZD3的主音量旋钮可开机，此时屏幕将点亮，并进入上次使用的输入模式。
2. 单击ZD3或遥控器上的"🔇"按钮可静音，音量将逐渐降低至零。再次单击可取消静音，音量将恢复至之前设置的音量。
3. 长按主音量旋钮约3秒钟可关机。

音量设置
1. 静音/取消静音：按遥控器上的"🔇"按钮可静音ZD3。静音状态下，屏幕角落会显示静音图标。再次按下可取消静音。

2. 音量调节：使用遥控器按钮"+"和"-"按钮或遥控器调节ZD3的音量。

注意：使用旁路模式时，ZD3仅作为DAC运行，音量固定为0分贝，无法调节音量。

旁路模式

1. 启用旁路模式后，ZD3进入纯DAC模式。在此配置下，ZD3专门以高质量数字信号转换为模拟信号，绕过其他所有处理功能。确保放大器或有源音箱处于关闭状态，以防设备损坏。

2. 关闭旁路模式后，ZD3切换至DAC+前置放大器模式，可通过音量旋钮调节音量。

入力と出力の接続

1. 電源アンプまたはアクティブスピーカーを接続。
2. デジタル音声ソース（コンピュータ、スマートスピーカーなど）を接続。

ご注意：
アンプまたは電源をオフにしてから接続することでスピーカーの損傷を防ぎます。

Bluetooth入力モード

1. 音量調整ノブを短押しするか、リモコンの「Source」ボタンを押すと、ペアリングモードに入ります。画面上部に「PAIRING」と表示されます。

2. 携帯、PC などのデバイスで「Bluetooth 設定」を開き、「FOSI Audio ZD3」を検索してペアリングを開始します。ペアリングが完了すると、画面に「CONNECTED」と表示されます。

3. 音量調整ノブをダブルクリックすると、Bluetooth ペアリング情報を削除し、Bluetooth ペアリングモードに入ります。

光入力モード

1. 光ケーブルの一端を ZD3 に接続し、もう一端を出力デバイスに接続します。
2. 音量調整ノブを短押しするか、リモコンの「OPT」ボタンを押すと、光入力モードに切り替わります。画面上部に現在のモードの名称が表示されます。

同軸入力モード

1. 同軸ケーブルの一端を ZD3 に接続し、もう一端を出力デバイスに接続します。
2. 音量調整ノブを短押しするか、リモコンの「COAX」ボタンを押すと、同軸入力モードに切り替わります。画面上部に現在のモードの名称が表示されます。

HDMI(ARC)入力モード

1. HDMI ケーブルの一端を ZD3 に接続し、もう一端を出力デバイスに接続します。
2. 音量調整ノブを短押しするか、リモコンの「HDMI」ボタンを押すと、HDMI 入力モードに切り替わります。画面上部に現在のモードの名称が表示されます。

3. ZD3 は、「HDMI 強制 ARC」機能をサポートしています。ZD3 および出力デバイスが HDMI モードに設定されている場合、音量同期コントロールが有効になります。

ご注意：
ZD3 に接続されている出力デバイスのみが、ZD3 の電源オン/オフを制御できます。ZD3 に接続されている出力デバイスは、ZD3 の電源オン/オフを同時に制御することはできません。

USB入力モード

1. 付属の USB ケーブルを使用してデバイスを接続します。
2. 音量調整ノブを短押しするか、リモコンの「USB」ボタンを押すと、USB 入力モードに切り替わります。画面上部に現在のモードの名称が表示されます。

重要：
1. ZD3 を PC の USB デコーダーとして使用するにはどうすればよいですか？
[Windows]
Windows 8/10/11 システムは、ドライバレスプラグアンドプレイをサポートしています。
付属の USB ケーブルを使用して ZD3 を PC に接続します。
[ビデオ] ZD3 を PC の音声出力として使用します。
[Mac/iOS]
Macbook は、ドライバレスプラグアンドプレイをサポートしています。ZD3 を Macbook に接続し、出力デバイスとして Fosi Audio ZD3 を選択するだけです。

2. Windows システムで ZD3 を使用する場合、パフォーマンスを保証するためにドライバーをインストールする必要があります。
1.PC のオペレーティングシステムは Windows 7 以前のバージョンです。
2.DSD 音楽ファイルを再生しています。
3.ASIO ドライバを使用してシステムをバイパスし、結果として生じるミキサープラグインを使用して DSD を再生する場合、追加のドライバをインストールする必要はありません。
4.PCM 768kHz の音楽ファイルを再生しています。
5.ASIO ドライバを使用してシステムをバイパスしています。
注：Windows システムは、排他的モードでの音量制御をサポートしない場合があります。

旅行ガイド

注意：
1. 接続が完了するまで電源を入れないでください。
2. 音楽を再生する前に、音量が低いことを確認してください。音量が大きすぎると、聞こえにくくなったり、聴覚を損ねたりする恐れがあります。

電源のオン/オフ
1. ZD3の主音量ノブを短押しすると、電源がオンになります。画面が点灯し、デバイスは最後に使用した入力モードに切り替わります。
2. ZD3またはリモコンを一度クリックすると、音量がゼロまで徐々に下がります。もう一度クリックすると、音量が復帰します。
3. ZD3の主音量ノブを長押しすると、電源がオフになります。

音量セット
1. ミュート/ミュート解除：リモコンの「🔇」ボタンを押すと、ZD3 をミュートします。ミュートされると、画面の角にミュートアイコンが表示されます。もう一度押すとミュートが解除されます。

2. 音量調整：リモコンの「+」および「-」ボタンまたはリモコンを使用して ZD3 の音量を調整することができます。

ご注意：
バイパスモードの場合、ZD3 は純粋な DAC として動作し、音量は 0 dB に固定されており調整することはできません。

Bypassモード

1. Bypassモードをアクティブにすると、ZD3は純粋なDACモードになります。この構成では、ZD3は専ら高品質デジタル信号をアナログ信号に変換することに特化し、他の処理機能はすべてバイパスします。アンプまたはアクティブスピーカーを電源オフにしてから接続することで、機器への損傷を防ぎます。

2. Bypassモードをオフにすると、ZD3はDAC+プリアンプモードに切り替わり、音量調ノブで音量を調整することができます。

製品について

Fosi Audio ZD3 ハイファイ・ステレオ・ディーコーダー（DAC）をご購入頂き誠にありがとうございます。

ZD3はFosi Audioがユーザーのご要望を深く理解した上で作成に取組む。ESS社のES9038Q2M（ES9038Q2M+ES9038Q2M）チップを搭載し、PCM（384kHz/32bit）までのデコードをサポートします。ZD3はJitter除去回路とバランス型アナログ回路を採用しています。また、ZD3はFosi Audioが独自に開発したジッタ除去回路とバランス型アナログ回路を採用しています。また、高品質の電解コンデンサと低ドリフト電解コンデンサを搭載しています。これらの高品質部品は、信号処理誤差を最小限に抑えるとともに、信号の純度を保証します。USB、同軸、光ファイバーなどの接続オプションを搭載しているZD3は、HiFiの世界へ皆様を誘う素晴らしい旅になることを確信しています。ご購入ありがとうございます。Fosi Audioは、お客様の音質を保つため、より高品質な製品をご提供するよう努力しています。

製品保証

Fosi Audio は、購入日から 24 ヶ月の限定保証サポートを提供することを約束します。製品の保証期間内に問題が発生した場合、サポートチームに連絡してください。**support@fosiaudio.com** までご連絡ください。

当社について

Fosi Audio は、あらゆる情熱と専門知識を注ぎ、革新的なオーディオ製品を設計・開発しています。最高の音質、便利な接続性、および私たちが最も重要な機能を提供することを目的としています。私たちの品質への取り組みは、最近、お客様がこれらの製品を楽しんでいただけるのと同じくらい、これらを作成することに力を注いでいます。

公式サイト： www.fosiaudio.com
Amazon ストア：https://www.amazon.co.jp/fosiaudio
Facebook ページ：www.facebook.com/fosiaudioglobal
YouTube チャンネル：www.youtube.com/@fosiaudio
公式フォーラム：community.fosiaudio.com
ツイッター（Twitter）：https://twitter.com/fosiaudio_JP
クラウドサービス及びカスタマーサポートEmail：
support@fosiaudio.com

Scan for more

よくある質問

1.オーディオシステムができましたが、音が出ません。
● 電源インジケーターが点灯しているかどうかを確認してください。
● 音量が低すぎる場合は、音量を徐々に上げてください。
● Bluetooth を使用している場合は、デバイスがペアリングされていることを確認してください。
● オーディオケーブルが正しくないか、または接続が緩んでいる場合は、接続を確認してください。

2.USB が認識されません。
● 別の USB ポートを試してください。
● ケーブルが緩んでいる場合は、USB ケーブルを交換してください。
● コンピュータの誤作動が発生している場合は、コンピュータを確認するか、別のコンピュータを使用してください。
● 電源が不足している場合は、電源が入っている USB ポートに接続してください。

公式ウェブサイト：www.fosiaudio.com
Amazon ストア：https://www.amazon.co.jp/fosiaudio
Facebook ページ：www.facebook.com/fosiaudioglobal
YouTube チャンネル：www.youtube.com/@fosiaudio
公式フォーラム：community.fosiaudio.com
ツイッター（Twitter）：https://twitter.com/fosiaudio_JP
クラウドサービス及びカスタマーサポートEmail：
support@fosiaudio.com

Scan for more