

# **B850 MLG EDITION**

**Motherboard** 

User Guide

## **Contents**


Quick Start	4
Specifications	17
Special Features	21
Package Contents	22
Back Panel Connectors	23
LAN Port LED Status Table	24
Audio Jacks Connection	24
Installing Antenna	26
Overview of Components	27
CPU Socket	28
DDR5 DIMM Slots	30
PCI_E1~3: PCIe Expansion Slots	32
M2_1~4: M.2 Slots (Key M)	33
SATA_A1~A4: SATA 6Gb/s Connectors	39
JAUD1: Front Audio Connector	39
JFP1, JFP2: Front Panel Connectors	40
CPU_PWR1~2, ATX_PWR1, PCIE_PWR1: Power Connectors	41
JCI1: Chassis Intrusion Connector	42
JUSBC1: USB 20Gbps Type-C Front Panel Connectors	43
JUSB2~3: USB 5Gbps Connectors	43
JUSB4~5: USB 2.0 Connectors	44
JTPM1: TPM Module Connector	44
JOC_FS1: Safe Boot Jumper	45
JBAT1: Clear CMOS (Reset BIOS) Jumper	45
CPU_FAN1, PUMP_SYS1, SYS_FAN1~6: Fan Connectors	46
JRGB1: RGB LED connector	47
JARGB_V2_1~3: A-RAINBOW V2 (ARGB Gen2) LED connectors	48
JAF_2: EZ Conn-Header V2	49
Onboard LEDs	51
EZ Debug LED	51
EZ Memory Detection LED	51
JPWRLED1: LED power input	51
EZ Digi-Debug LED	52
Boot Phases	52
EZ Digi-Debug LED Table	52

Installing OS, Drivers & MSI Center	57
Installing Drivers with MSI Driver Utility Installer	58
UEFI BIOS	61
BIOS Setup	
Entering BIOS Setup	
Resetting BIOS	64
Updating BIOS	64
Block Diagram	66
Regulatory Notices	
1.050.0001 j 110.0000	

## **Quick Start**

This Quick Start provides clear diagrams to help you install the motherboard. Video demonstrations are also available for some installations. Visit these videos by clicking the provided URL on your phone or tablet's web browser. Alternatively, you can scan the QR code to access the video directly.

## **Preparing Tools and Components**



A Package of Screws

## **Safety Information**


- The components included in this package are prone to damage from electrostatic discharge (ESD). Please adhere to the following instructions to ensure successful computer assembly.
- Ensure that all components are securely connected. Loose connections may cause the computer to not recognize a component or fail to start.
- Hold the motherboard by the edges to avoid touching sensitive components.
- It is recommended to wear an electrostatic discharge (ESD) wrist strap when
  handling the motherboard to prevent electrostatic damage. If an ESD wrist strap
  is not available, discharge yourself of static electricity by touching another metal
  object before handling the motherboard.
- Store the motherboard in an electrostatic shielding container or on an anti-static pad whenever the motherboard is not installed.
- Before turning on the computer, ensure that there are no loose screws or metal components on the motherboard or anywhere within the computer case.
- Do not boot the computer before installation is completed. This could cause permanent damage to the components as well as injury to the user.
- If you need help during any installation step, please consult a certified computer technician.
- Always turn off the power supply and unplug the power cord from the power outlet before installing or removing any computer component.
- Keep this user guide for future reference.
- Keep this motherboard away from humidity.
- Make sure that your electrical outlet provides the same voltage as is indicated on the PSU, before connecting the PSU to the electrical outlet.
- Place the power cord such a way that people can not step on it. Do not place anything over the power cord.
- All cautions and warnings on the motherboard should be noted.
- If any of the following situations arises, get the motherboard checked by service personnel:
  - Liquid has penetrated into the computer.
  - The motherboard has been exposed to moisture.
  - The motherboard does not work well or you can not get it work according to user guide.
  - The motherboard has been dropped and damaged.
  - The motherboard has obvious sign of breakage.
- Do not leave this motherboard in an environment above 60°C (140°F), it may damage the motherboard

### Case stand-off notification


To prevent damage to the motherboard, any unnecessary mounting stand-off between the motherboard circuits and the computer case is prohibited. The Case standoff keep out zone signs will be marked on the backside of motherboard (as shown below) to serve as a warning to user.

### **Avoid collision notification**

Protective paint is printed around each screw hole to prevent parts from being scratched.




<sup>\*</sup> The illustration above is for reference only and may vary from the motherboard you purchased.





If you are installing the screw-type CPU heatsink, please follow the figure below to remove the retention module first and then install the heatsink.





## **Installing DDR5 memory**





• https://msi.gm/S647FF99






## **Connecting the Front Panel Header**






• https://msi.gm/S8EF7577



## Installing the Motherboard





## **Connecting the Power Connectors**








• https://msi.gm/SD937E2C














## **Installing a Graphics Card**



# **Connecting Peripheral Devices**



## **Power On**



# **Specifications**

CPU	Supports AMD Ryzen™ 9000/ 8000/ 7000 Series Desktop Processors*			
CFO	Processor socket AM5			
	* Please go to www.msi.com to get the newest support status as new processors are released.			
Chipset	AMD B850 Chipset			
	• 4x DDR5 memory slots*, supporting up to 256GB**			
	Supports AMD POR Speed and JEDEC Speed			
	Supports Memory Overclocking and AMD EXPO™			
	Supports Dual-Channel mode			
	Supports Non-ECC, Un-buffered memory			
Memory	Supports CUDIMM, Clock Driver bypass mode only***			
	* The DIMM slots on this motherboard only have single-sided latches.			
	** Memory compatibility and supported speeds can vary depending on the CPU and memory configuration. For detailed information, please refer to the Memory Compatibility List available on the product's Support page or visit https://www.msi.com/support/.			
	*** CUDIMM support and POR boot frequency may vary by CPU series, with manual overclocking available after boot. Certain CPUs may fail to boot, but future BIOS updates will improve compatibility.			
	3x PCIe x16 slots			
	3x PCIe x16 slots     PCI_E1 slot (From CPU)			
	<ul> <li>PCI_E1 slot (From CPU)</li> <li>Supports PCIe 5.0 x16 (For Ryzen™ 9000/ 7000 Series</li> </ul>			
Expansion Slots	<ul> <li>PCI_E1 slot (From CPU)</li> <li>Supports PCIe 5.0 x16 (For Ryzen™ 9000/ 7000 Series processors)</li> <li>Supports PCIe 4.0 x8 (For Ryzen™ 8700/ 8600/ 8400</li> </ul>			
Expansion Slots	<ul> <li>PCI_E1 slot (From CPU)</li> <li>Supports PCIe 5.0 x16 (For Ryzen™ 9000/ 7000 Series processors)</li> <li>Supports PCIe 4.0 x8 (For Ryzen™ 8700/ 8600/ 8400 Series processors) Support</li> <li>Supports PCIe 4.0x4 (For Ryzen™ 8500/ 8300 Series</li> </ul>			
Expansion Slots	<ul> <li>PCI_E1 slot (From CPU)</li> <li>Supports PCIe 5.0 x16 (For Ryzen™ 9000/ 7000 Series processors)</li> <li>Supports PCIe 4.0 x8 (For Ryzen™ 8700/ 8600/ 8400 Series processors) Support</li> <li>Supports PCIe 4.0x4 (For Ryzen™ 8500/ 8300 Series processors)</li> </ul>			
Expansion Slots	<ul> <li>PCI_E1 slot (From CPU)</li> <li>Supports PCIe 5.0 x16 (For Ryzen™ 9000/ 7000 Series processors)</li> <li>Supports PCIe 4.0 x8 (For Ryzen™ 8700/ 8600/ 8400 Series processors) Support</li> <li>Supports PCIe 4.0x4 (For Ryzen™ 8500/ 8300 Series processors)</li> <li>PCI_E2 slot (From B850 chipset)</li> </ul>			
Expansion Slots	<ul> <li>PCI_E1 slot (From CPU)</li> <li>Supports PCIe 5.0 x16 (For Ryzen™ 9000/ 7000 Series processors)</li> <li>Supports PCIe 4.0 x8 (For Ryzen™ 8700/ 8600/ 8400 Series processors) Support</li> <li>Supports PCIe 4.0x4 (For Ryzen™ 8500/ 8300 Series processors)</li> <li>PCI_E2 slot (From B850 chipset)</li> <li>Supports up to PCIe 3.0 x1</li> </ul>			
Expansion Slots	<ul> <li>PCI_E1 slot (From CPU)</li> <li>Supports PCIe 5.0 x16 (For Ryzen™ 9000/ 7000 Series processors)</li> <li>Supports PCIe 4.0 x8 (For Ryzen™ 8700/ 8600/ 8400 Series processors) Support</li> <li>Supports PCIe 4.0x4 (For Ryzen™ 8500/ 8300 Series processors)</li> <li>PCI_E2 slot (From B850 chipset)</li> <li>Supports up to PCIe 3.0 x1</li> <li>PCI_E3* slot (From B850 chipset)</li> </ul>			
	<ul> <li>PCI_E1 slot (From CPU)</li> <li>Supports PCIe 5.0 x16 (For Ryzen™ 9000/ 7000 Series processors)</li> <li>Supports PCIe 4.0 x8 (For Ryzen™ 8700/ 8600/ 8400 Series processors) Support</li> <li>Supports PCIe 4.0x4 (For Ryzen™ 8500/ 8300 Series processors)</li> <li>PCI_E2 slot (From B850 chipset)</li> <li>Supports up to PCIe 3.0 x1</li> <li>PCI_E3* slot (From B850 chipset)</li> <li>Supports up to PCIe 4.0 x4</li> </ul>			
Expansion Slots Onboard Graphics	<ul> <li>PCI_E1 slot (From CPU)</li> <li>Supports PCIe 5.0 x16 (For Ryzen™ 9000/ 7000 Series processors)</li> <li>Supports PCIe 4.0 x8 (For Ryzen™ 8700/ 8600/ 8400 Series processors) Support</li> <li>Supports PCIe 4.0x4 (For Ryzen™ 8500/ 8300 Series processors)</li> <li>PCI_E2 slot (From B850 chipset)</li> <li>Supports up to PCIe 3.0 x1</li> <li>PCI_E3* slot (From B850 chipset)</li> <li>Supports up to PCIe 4.0 x4</li> <li>*PCI_E3 slot will run at x2 speed when installing device in the M2_3 slot.</li> <li>1x HDMI™ 2.1 with FRL port, supporting a maximum resolution of 4K 120Hz or 8K 60Hz*/ **</li> <li>*Available only on processors featuring integrated graphics.</li> </ul>			
	<ul> <li>PCI_E1 slot (From CPU)</li> <li>Supports PCIe 5.0 x16 (For Ryzen™ 9000/ 7000 Series processors)</li> <li>Supports PCIe 4.0 x8 (For Ryzen™ 8700/ 8600/ 8400 Series processors) Support</li> <li>Supports PCIe 4.0x4 (For Ryzen™ 8500/ 8300 Series processors)</li> <li>PCI_E2 slot (From B850 chipset)</li> <li>Supports up to PCIe 3.0 x1</li> <li>PCI_E3* slot (From B850 chipset)</li> <li>Supports up to PCIe 4.0 x4</li> <li>*PCI_E3 slot will run at x2 speed when installing device in the M2_3 slot.</li> <li>1x HDMI™ 2.1 with FRL port, supporting a maximum resolution of 4K 120Hz or 8K 60Hz*/ **</li> </ul>			

Continued on next column

## Continued from previous column

	• 4x M.2 slots (Key M)			
	M2_1 slot (From CPU)			
	<ul> <li>Supports up to PCIe 5.0 x4 (For Ryzen™ 9000/ 7000Series processors)</li> </ul>			
	<ul> <li>Supports up to PCIe 4.0 x4 (For Ryzen™ 8000 Series processors)</li> </ul>			
	<ul> <li>Supports 2280/ 22110 storage devices</li> </ul>			
	M2_2 slot (From CPU)			
	<ul> <li>Supports up to PCle 5.0 x4 (For Ryzen<sup>™</sup> 9000/ 7000 Series)</li> </ul>			
M.2 SSD Slots	<ul> <li>Supports up to PCIe 4.0 x4 (For Ryzen™ 8700/8600/ 8400 Series processors)</li> </ul>			
	<ul> <li>Supports up to PCIe 4.0 x2 (For Ryzen™ 8500/ 8300 Series processors)</li> </ul>			
	<ul> <li>Supports 2260/ 2280 storage devices</li> </ul>			
	<ul> <li>M2_3* slot (From Chipset)</li> </ul>			
	• Supports up to PCle 4.0 x2			
	<ul> <li>Supports 2260/2280 storage devices</li> </ul>			
	M2_4 slot (From Chipset)			
	<ul> <li>Supports up to PCle 4.0 x4</li> </ul>			
	<ul> <li>Supports 2260/2280 storage devices</li> </ul>			
	* PCI_E3 slot will run at x2 speed when installing device in the M2_3 slot.			
RAID	Supports RAID 0, RAID 1 and RAID 10* for M.2 NVMe storage devices			
וחוט	* RAID 10 for M.2 NVMe storage devices is only supported by AMD Ryzen™ 9000/7000 series CPU.			
	• Realtek® ALC4080 Codec			
Audio	• 7.1-Channel USB High Performance Audio			
Audio	Supports up to 32-Bit/384 kHz playback on front panel			
	Supports S/PDIF output			
LAN	• 1x Realtek® 8126 5Gbps LAN controller			
	'			

Continued on next column

## Continued from previous column

Wi-Fi & Bluetooth®	Wi-Fi 7  The Wireless module is pre-installed in the M.2 (Key-E)slot  Supports MU-MIMO TX/RX, 2.4GHz/5GHz/6GHz* (320MHz) up to 5.8Gbps  Supports 802.11 a/ b/ g/ n/ ac/ ax/ be  Supports Bluetooth® 5.4**, MLO, 4KQAM  6GHz band support may depend on every country's regulations and Wi-Fi 7 will be ready in Windows 11 version 24H2.  **The Bluetooth version may be updated, please refer to the Wi-Fi chipset vendor's website for details. Bluetooth 5.4 will be ready in Windows 11 version 24H2.			
Power Connectors	<ul> <li>1x 24-pin ATX main power connector</li> <li>2x 8-pin +12V power connectors</li> <li>1x 8-pin PCle power connector</li> </ul>			
<ul> <li>1x USB 20Gbps Type-C front panel port (From B850 chipset)</li> <li>2x USB 5Gbps connectors (From Hub GL3523)</li> <li>Supports additional 4 USB 5Gbps ports</li> <li>2x USB 2.0 connectors (From B850 chipset)</li> <li>Supports additional 4 USB 2.0 ports</li> </ul>				
Fan Connectors	<ul> <li>1x 4-pin CPU fan connector</li> <li>1x 4-pin water-pump/ system fan connector</li> <li>6x 4-pin system fan connectors</li> </ul>			
System Connectors	<ul> <li>1x Front panel audio connector</li> <li>2x System panel connectors</li> <li>1x Chassis Intrusion connector</li> <li>1x TPM module connector</li> <li>1x EZ Conn-Header V2 (JAF_2)</li> </ul>			
Jumpers	<ul><li>1x Clear CMOS jumper</li><li>1x OC safe boot jumper</li></ul>			
• 1x 4-pin RGB LED connector • 3x 3-pin A-RAINBOW V2 (ARGB Gen2) LED connectors • 4x EZ Debug LED • 1x EZ Memory Detection LED • 1x EZ Digi-Debug LED				

Continued on next column

## Continued from previous column

Back Panel Connectors & Others	<ul> <li>1x Clear CMOS Button</li> <li>1x Flash BIOS Button</li> <li>1x HDMI™ port</li> <li>3x USB 10Gbps Type-C ports (From CPU)</li> <li>2x USB 10Gbps Type A port (From CPU &amp; B850 Chipset)</li> <li>1x USB 5Gbps Type A (From B850 Chipset)</li> <li>4x USB 2.0 connectors (From HUBGL850)</li> <li>1x 5G LAN (RJ45) port</li> <li>2x Wi-Fi antenna connectors</li> <li>2x audio jacks</li> <li>1x Optical S/PDIF Out connector</li> </ul>
I/O Controller	NUVOTON NCT6687-R Controller Chip
Hardware Monitor	<ul> <li>CPU/ System/ Chipset temperature detection</li> <li>CPU/ System/ Pump fan speed detection</li> <li>CPU/ System/ Pump fan speed control</li> </ul>
Form Factor	ATX Form Factor     9.6 in. x 12 in. (244 mm x 305 mm)
BIOS Features	<ul> <li>1x 256 Mb flash</li> <li>UEFI AMI BIOS</li> <li>ACPI 6.5, SMBIOS 3.7</li> <li>Multi-language</li> </ul>
Software	<ul> <li>Drivers</li> <li>MSI Center</li> <li>Acrobat</li> <li>Adobe Creative Cloud</li> <li>AIDA64 Extreme - MSI Edition</li> <li>CPU-Z MSI GAMING</li> <li>Dropbox</li> <li>MSI App Player(BlueStacks)</li> <li>Norton 360</li> </ul>

## **Special Features**

#### **MSI Center**

- MSI AI Engine
- · Game Highlights
- · Cooling Wizard
- Mystic Light
- Ambient Link
- Frozr AI Cooling
- · Hardware Monitoring
- · Live Update
- MSI Companion
- System Diagnosis
- True Color
- User Scenario
- AI LAN Manager

#### **EZ DIY**

- EZ M.2 Sheild Frozr II
- EZ M.2 Clip II
- EZ PCIe Release
- Flash BIOS Button
- Clear CMOS Button
- Pre-installed I/O Shield
- F7 Antenna
- EZ Front Panel Cable
- EZ Conn-Design
- PCI-E Steel Armor II
- EZ Digi-Debug LED
- EZ DEBUG LED
- EZ Meomory Detection LED
- EZ LED Control

#### Thermal Features

- Extended Heatsink Design
- M.2 Shield Frozr
- 7W/mK MOSFET thermal pad
- · Choke thermal pad
- Combo\_Fan Header
- FAN Headers (CPU\*1 + PUMP\_SYS\*1 + SYSTEM\*6)

#### Performance

- Core Boost
- VRM Design
- Dual CPU Power
- Lightning Gen 5 PCI-E Slot
- Lightning Gen 5 M.2 Slot
- Lightning Gen 4 PCI-E Slot
- Lightning Gen 4 M.2 Slot
- · Front USB Type-C
- Supplemental PCIe Power Connector
- Server Grade PCB
- 2oz Copper thickened PCB

#### Audio

Audio Boost 5

#### **RGB Support**

- Mystic Light
- Mystic Light Extension (RGB)
- Mystic Light Extension (ARGB V2)
- Ambient Devices Support

#### BIOS

- Click BIOS X
- Al Boost
- Performance Preset

## **Package Contents**

Please check the contents of your motherboard package. It should contain:

#### **Board**

• 1x Motherboard

#### Documentation

- 1x Quick installation guide
- 1x European Union Regulatory Notices

#### Cables

- 1x SATA cable
- 1x 1 to 3 EZ Conn-Cable (V2)
- 1x EZ Front panel cable

#### Accessories


- 1x EZ Wi-Fi Antenna
- 1x Cable sticker
- 3x EZ M.2 Clip II
- 1x EZ M.2 Clip II Remover



## /!\ Important


If any of the above items are damaged or missing, please contact your retailer.

# **Back Panel Connectors**



Item	Description
1	Flash BIOS button - Please refer to page 65 for details about updating BIOS with Flash BIOS button.
2	USB 10Gbps Type C ports (From CPU)
3	USB 10Gbps Type-C port (From CPU)
4	USB 10Gbps Type-A port (From B850 Chipset)
5	Wi-Fi antenna connectors
6	Optical S/PDIF Out connector
7	Clear CMOS button - Power off your computer. Press and hold the Clear CMOS button for about 5-10 seconds to reset BIOS to default values.
8	HDMI <sup>TM</sup> port High-definition multimedia interface
9	USB 10Gbps Type-A port (From CPU) • Flash BIOS port
10	USB 5Gbps Type-A port (From B850 Chipset)
11	USB 2.0 Type-A ports (From HUBGL850)
12	5Gbps LAN(RJ45) port
13	Line-out port
14	Mic-in port


## **LAN Port LED Status Table**




Link/ Activity LED		Speed LED	
Status	Description	Status	Speed
Off	No link	Off	10Mbps
Yellow blinking slowly	Linked	Green	100Mbps/ 1Gbps/ 2.5Gbps
Yellow blinking rapidly	Data activity	Orange	5Gbps

## **Audio Jacks Connection**


## Audio jacks to headphone and microphone diagram




## Audio jacks to stereo speakers diagram




## Audio jacks to 4-channel speakers diagram



Audio jacks to 5.1-channel speakers diagram




Audio jacks to 7.1-channel speakers diagram




## **Installing Antenna**


- 1. Combine the antenna with the base.
- 2. Plug two antenna cables tight to the WiFi antenna connectors as shown.



3. Place the antenna as high as possible for a better signal.




# **Overview of Components**



### **CPU Socket**


The AM5 socket is a modern CPU socket designed for AMD processors. It is a key component in contemporary computing systems, providing the foundation for powerful and efficient CPUs.



### Installing the CPU to the AM5 socket

The surface of the AM5 CPU has **two notches** and a **golden triangle** to assist in correctly lining up the CPU for motherboard placement. The golden triangle is the Pin 1 indicator.

To install the CPU, align the two notches on the AM5 socket with the two corresponding notches on the CPU. Please ensure that the gold triangle on the CPU serves as the PIN 1 indicator during the installation process.




Distance from the center of the CPU socket to the nearest DIMM slot.


## Important

- When changing the processor, the system configuration could be cleared and reset BIOS to default values, due to the AM5 processor's architecture.
- Please ensure that the motherboard and power supply are turned off and always disconnect the power cord from the power outlet before installing or removing the CPU.
- Please retain the CPU protective cap after installing the processor. MSI will deal with Return Merchandise Authorization (RMA) requests if only the motherboard comes with the protective cap on the CPU socket.
- Whenever the CPU is not installed, always protect the CPU socket pins by covering the socket with the protective cap.
- The CPU should only fit in one orientation, so do not force it. Gently place the CPU into the socket without applying excessive pressure.
- Please handle the CPU by the edges only; avoid touching the pins or the surface of the CPU. Any damage to the pins can result in a malfunctioning CPU.
- When installing a CPU, always remember to install a CPU heatsink. A CPU heatsink is necessary to prevent overheating and maintain system stability.
- Please install the CPU cooler according to the manufacturer's instructions. Make sure it is securely a tight seal with the CPU and attached to the motherboard to ensure proper heat dissipation.
- Overheating can seriously damage the CPU and motherboard. Always make sure the
  cooling fans work properly to protect the CPU from overheating. Be sure to apply an
  even layer of thermal paste (or thermal tape) between the CPU and the heatsink to
  enhance heat dissipation.
- This motherboard is designed to support overclocking. Before attempting to overclock, please make sure that all other system components can tolerate overclocking. Any attempt to operate beyond product specifications is not recommended. MSI® does not guarantee the damages or risks caused by inadequate operation beyond product specifications.


### **DDR5 DIMM Slots**

The DDR5 DIMM slot is a dedicated connector designed to accommodate DDR5 (Double Data Rate 5) memory modules. It represents the latest standard in computer memory, providing enhanced data transfer speeds and efficiency.






## Memory module installation recommendation





Always insert memory modules in the DIMMA2 slot first.






### **Important**

- The DIMM slots on this motherboard only have a single latch. Please be careful when installing or removing memory modules to avoid damaging the slots.
- Align the notch on the DDR5 module with the notch on the memory slot to ensure proper orientation. Do not force the module into the slot; it should slide in easily if properly aligned.
- To ensure system stability for Dual channel mode, memory modules must be of the same type, number and density.
- Some memory modules may operate at a lower frequency than the marked value when overclocking due to the memory frequency operates dependent on its Serial Presence Detect (SPD). Go to BIOS and find the **DRAM Speed** to set the memory frequency if you want to operate the memory at the marked or at a higher frequency.
- It is recommended to use a more efficient memory cooling system for full DIMMs installation or overclocking.
- The stability and compatibility of installed memory module depend on installed CPU and devices when overclocking.
- Please refer to www.msi.com for more information on compatible memory.

## PCI\_E1~3: PCIe Expansion Slots

PCI Express (PCIe) expansion slots are used to connect add-on cards to the motherboard. These cards can provide additional functionality to your computer, such as graphics, networking, or storage.






## Important

- If you install a large and heavy graphics card, you need to use a tool such as MSI Graphics Card Bolster to support its weight to prevent deformation of the slot.
- For a single PCIe x16 expansion card installation with optimum performance, using the **PCI\_E1** slot is recommended.
- When adding or removing expansion cards, always turn off the power supply and unplug the power supply power cable from the power outlet. Read the expansion card's documentation to check for any necessary additional hardware or software changes.

## M2\_1~4: M.2 Slots (Key M)

The M.2 slot is a small, high-speed expansion slot on a motherboard. It can be used to connect an M.2 SSD, which is a type of solid-state drive that offers faster performance than traditional SATA SSDs.



Watch the video to learn how to Install M.2 SSD with Screwless M.2 Shield Frozr heatsink.





https://msi.gm/S7F5D000




#### **Important**

If your M.2 SSD equips its own heatsink, please note the following:

- Remove the M.2 plate or rubber cube in the M.2 slot before installing M.2 SSD. Do not re-install the heatsink supplied with the motherboard.
- Ensure that the M.2 SSD heatsink you use fits the size limits to prevent damage.


#### M.2 SSD Heatsink Size Restrictions

If you need to purchase an additional heatsink, please refer to the diagram below to confirm the M.2 installation space dimensions. Please also consider the height of the installed PCIe expansion card when determining M.2 installation space.




## Installing M.2 module into M2\_1 slot


1. Press and hold the end button of Screwless M.2 Shield Frozr heatsink.




2. Slightly lift up the end part of Screwless M.2 Shield Frozr heatsink and move it forward to uninstall the heatsink.




3. Remove the protective film from the M.2 thermal pads on the M.2 plate.




**4.** If you install 22110 SSD, remove the installed **EZ M.2 Clip II** from 2280 screw hole by using the included **EZ M.2 Clip II Remover**. Skip this step if you install 2280 SSD.



- 5. Insert your M.2 SSD into the M.2 slot at a 30-degree angle.
- **6.** Rotate the EZ M.2 Clip to secure the M.2 SSD, or use the EZ M.2 Clip II, which automatically locks and secures the SSD.




- 7. Remove the protective films from the thermal pads under Screwless M.2 Shield Frozr heatsink.
- **8.** Align the notches under Screwless M.2 Shield Frozr heatsink with the tenons, and then put the heatsink back in place.
- 9. Press the end side of Screwless M.2 Shield Frozr heatsink to lock it completely.




# Installing M.2 module into M2\_2~M2\_4 slots


- 1. Loosen the screws of M.2 Shield Frozr heatsink.
- 2. Lift up the M.2 Shield Frozr heatsink and remove it.




3. If you install 2260 SSD, please use the included **EZ M.2 Clip II Remover** to install the included **EZ M.2 Clip II** in the screw hole. Skip this step if you install 2280 SSD.



- 4. Insert your M.2 SSD into the M.2 slot at a 30-degree angle.
- 5. Rotate the EZ M.2 Clip to secure the M.2 SSD, or use the EZ M.2 Clip II, which automatically locks and secures the SSD.



- Remove the protective film from the thermal pad under the M.2 Shield Frozr heatsink.
- 7. Put the M.2 Shield Frozr heatsink back in place and secure it.




# Removing M.2 SSD using the EZ M.2 Clip II


To remove M.2 SSD from the EZ M.2 Clip II, gently push the spring head on the top of the EZ M.2 Clip II outward while simultaneously pulling the M.2 SSD out.



# SATA\_A1~A4: SATA 6Gb/s Connectors

These connectors are SATA 6Gb/s interface ports. Each connector can connect to one SATA device.








### // Important

- Please do not fold the SATA cable at a 90-degree angle. Data loss may result during transmission otherwise.
- SATA cables have identical plugs on either sides of the cable. However, it is recommended that the flat connector be connected to the motherboard for space saving purposes.

### **JAUD1: Front Audio Connector**

This connector allows you to connect audio jacks on the front panel.







Pin	Signal Name	Pin	Signal Name
1	MIC L	2	Ground
3	MIC R	4	NC
5	Head Phone R	6	MIC Detection
7	SENSE_SEND	8	No Pin
9	Head Phone L	10	Head Phone Detection

### JFP1, JFP2: Front Panel Connectors

The JFP1 connector controls the power on, power reset, and the LEDs on your PC case/chassis. Power Switch/ Reset Switch headers allow you to connect power button/ reset button. Power LED header connects to LED light on the PC case, and HDD LED header indicates the activity of the hard disk. The JFP2 connector is for Buzzer and Speaker. For connecting the cables from your PC case to the correct pins on the motherboard, please refer to the following images.








### Important

Make sure to connect the Power LED and HDD LED cables to the corresponding positive and negative pins on the motherboard. Otherwise, the LEDs will not function properly.


# **Using EZ Front Panel Cable**

The EZ Front Panel Cable allows you to first connect and integrate the PC case's front panel connectors, making it easier to install into the JFP1 connector. Attach Power SW, Reset SW, Power LED (+ to +, - to -), and HDD LED (+ to +, - to -) to the matching pins on the EZ Front Panel Cable, then plug the EZ Front Panel Cable into the JFP1 connector.



# CPU\_PWR1~2, ATX\_PWR1, PCIE\_PWR1: Power Connectors

These power connectors allow you to connect an ATX power supply.



#### CPU\_PWR1~2

Pin	Signal Name	Pin	Signal Name
1	Ground	2	Ground
3	Ground	4	Ground
5	+12V	6	+12V
7	+12V	8	+12V


#### ATX\_PWR1

Pin	Signal Name	Pin	Signal Name
1	+3.3V	2	+3.3V
3	Ground	4	+5V
5	Ground	6	+5V
7	Ground	8	PWR OK
9	5VSB	10	+12V
11	+12V	12	+3.3V
13	+3.3V	14	-12V
15	Ground	16	PS-ON#
17	Ground	18	Ground
19	Ground	20	Res
21	+5V	22	+5V
23	+5V	24	Ground

CPU\_PWR1



ATX PWR1



PCIE\_PWR1



PCIE\_PWR1

Pin	Signal Name	Pin	Signal Name
1	+12V	2	+12V
3	+12V	4	SENS1
5	Ground	6	SENS0
7	Ground	8	Ground




### 

Make sure that all the power cables are securely connected to a proper ATX power supply to ensure stable operation of the motherboard.

## **JCI1: Chassis Intrusion Connector**

This connector allows you to connect the chassis intrusion switch cable.



### Using chassis intrusion detector


- 1. Connect the JCI1 connector to the chassis intrusion switch/ sensor on the chassis.
- 2. Close the chassis cover.
- 3. Go to BIOS > Security > Chassis Intrusion Configuration.
- 4. Set Chassis Intrusion to Enabled.
- 5. Press F10 to save and exit and then press the Enter key to select Yes.
- **6.** Once the chassis cover is opened again, a warning message will be displayed on screen when the computer is turned on.

## Resetting the chassis intrusion warning

- 1. Go to BIOS > Security > Chassis Intrusion Configuration.
- 2. Set Chassis Intrusion to Reset.
- 3. Press F10 to save and exit and then press the Enter key to select Yes.


## JUSBC1: USB 20Gbps Type-C Front Panel Connectors

This USB connector allows you to connect to the USB Type-C® port on the front panel and supports data transfer speeds of up to 20Gbps. It features a user-friendly design that ensures proper orientation when connecting the cable.



## JUSB2~3: USB 5Gbps Connectors

These USB connectors allow you to connect to USB ports on the chassis panel and supports data transfer speeds of up to 5Gbps.



Pin	Signal Name	Pin	Signal Name
1	Power	2	USB3_RX_DN
3	USB3_RX_DP	4	Ground
5	USB3_TX_C_DN	6	USB3_TX_C_DP
7	Ground	8	USB2.0-
9	USB2.0+	10	Ground
11	USB2.0+	12	USB2.0-
13	Ground	14	USB3_TX_C_DP
15	USB3_TX_C_DN	16	Ground
17	USB3_RX_DP	18	USB3_RX_DN
19	Power	20	No Pin




### **Important**

Note that the Power and Ground pins must be connected correctly to avoid possible damage.

### JUSB4~5: USB 2.0 Connectors

These USB connectors allow you to connect to USB ports on the chassis panel and supports data transfer speeds of up to 480Mbps.





Pin	Signal Name	Pin	Signal Name
1	VCC	2	VCC
3	USB0-	4	USB1-
5	USB0+	6	USB1+
7	Ground	8	Ground
9	No Pin	10	NC




#### **Important**

- Note that the VCC and Ground pins must be connected correctly to avoid possible damage.
- In order to recharge your iPad, iPhone and iPod through USB ports, please install MSI Center utility.

### JTPM1: TPM Module Connector

This connector is designed for a Trusted Platform Module (TPM) to enable secure storage of sensitive data and perform cryptographic operations that ensure the integrity of your system.





Pin	Signal Name	Pin	Signal Name
1	SPI Power	2	SPI Chip Select
3	Master In Slave Out (SPI Data)	4	Master Out Slave In (SPI Data)
5	Reserved	6	SPI Clock
7	Ground	8	SPI Reset
9	Reserved	10	No Pin
11	Reserved	12	Interrupt Request




#### **Important**

The TPM module is not included and must be purchased separately.

### JOC\_FS1: Safe Boot Jumper

This jumper is used for Safe Boot. When this jumper is enabled, the system will boot with default settings and lower PCIe (from CPU) mode.




Normal (default)
Boot with the saved
BIOS settings.

Enabled
Apply the BIOS default settings and lower PCIe (from CPU) mode for Safe Boot

# JBAT1: Clear CMOS (Reset BIOS) Jumper

There is CMOS memory onboard that is external powered from a battery located on the motherboard to save system configuration data. If you want to clear the system configuration, set the jumpers to clear the CMOS memory.



Keep Data (default)



Clear CMOS/ Reset BIOS

### **Resetting BIOS to default values**

- 1. Power off the computer and unplug the power cord.
- 2. Use a jumper cap to short **JBAT1** for about 5-10 seconds.
- 3. Remove the jumper cap from JBAT1.
- 4. Plug the power cord and Power on the computer.

### CPU\_FAN1, PUMP\_SYS1, SYS\_FAN1~6: Fan Connectors


Fan connectors can be divided into two categories: PWM Mode and DC Mode. PWM Mode fan connectors provide a constant 12V output and adjust fan speed with a speed control signal. DC Mode fan connectors control fan speed by changing voltage. Please refer to the following specification table for the fan connector mode of your motherboard.

You can control fans in **BIOS> HARDWARE MONITOR** panel. Enabling Smart Fan Mode will regulate fan speed based on CPU or system temperature. Disabling Smart Fan Mode will set the fan to full speed.



### Important

You can set DC or PWM in **HARDWARE MONITOR** panel to your fan type if your motherboard supports it. Make sure fans are working properly after switching the PWM/ DC mode.





#### PWM Mode pin definition

Pin	Signal Name	Pin	Signal Name
1	Ground	2	+12V
3	Sense	4	Speed Control Signal

#### DC Mode pin definition

Pin	Signal Name	Pin	Signal Name
1	Ground	2	Voltage Control
3	Sense	4	NC

#### Fan specifications for fan connectors

Connector	Fan mode	Max. current	Max. power
CPU_FAN1	Auto mode	2A	24W
PUMP_SYS1	PWM mode	3A	36W
SYS_FAN1~6	Auto mode	1A	12W




### Important

The auto mode fan connectors can automatically detect PWM and DC modes.

### **JRGB1: RGB LED connector**


The JRGB connector allows you to connect the 5050 RGB LED strips 12V.






Pin	Signal Name	Pin	Signal Name
1	+12V	2	G
3	R	4	В

### **RGB LED Strip Connection**



#### **RGB LED Fan Connection**






## Important

- The JRGB connector supports up to 2 meters continuous 5050 RGB LED strips (12V/G/R/B) with the maximum power rating of 3A (12V).
- Always turn off the power supply and unplug the power cord from the power outlet before installing or removing the RGB LED strip.
- Please use MSI's software to control the extended LED strip.

### JARGB\_V2\_1~3: A-RAINBOW V2 (ARGB Gen2) LED connectors


The JARGB\_V2 connectors allow you to connect the ARGB Gen2 and the ARGB-based LED strips. The JARGB\_V2 connector supports up to 240 individually addressable RGB LEDs with maximum power rating of 3A (5V).






Pin	Signal Name	Pin	Signal Name
1	+5V	2	Data
3	No Pin	4	Ground

### **Addressable RGB LED Strip Connection**



#### Addressable RGB LED Fan Connection






Do not connect the wrong type of LED strips. The JRGB connector and the JARGB\_V2 connector provide different voltages, and connecting the ARGB 5V LED strip to the JRGB connector will result in damage to the LED strip.



- If you connect the ARGB Gen1 and ARGB Gen2 LED strips into the same connector, it
  may cause some issues. Please do not mix the ARGB Gen1 LED and the ARGB Gen2
  LED strips together.
- It is recommended that you install LED strips with the same specification to achieve the best effects.
- Always turn off the power supply and unplug the power cord from the power outlet before installing or removing the addressable RGB LED strip.
- Please use MSI's software to control the extended LED strip.

# JAF\_2: EZ Conn-Header V2


This header allows you to connect the ARGB Gen1 and Gen2 LED strips, fans and USB 2.0 devices. It can also be used to connect MPG EZ120 ARGB fans.






Pin	Signal Name	Pin	Signal Name
1	Ground	2	5V
3	12V	4	DATA
5	Sense	6	Ground
7	Speed	8	N/A
9	Ground	10	USB 2.0+
11	+5VSB	12	USB 2.0-

#### Addressable RGB LED Fan Connection



### MPG EZ120 ARGB Fan Connection






# !\ Important

- The Fan-JAF1 Cable is included in the packaging of MPG EZ120 ARGB.
- JAF\_2 header is compatible with JAF\_1 header since pins 1 to 7 carry the same signals. MPG EZ120 ARGB can be connected to the JAF\_2 header.
- For more information on how to install MPG EZ120 ARGB, please refer to https://msi. gm/S5035E56.

# **Onboard LEDs**

# **EZ Debug LED**


These LEDs indicate the debug status of the motherboard.



LED Color	Status
Red 🖪	CPU is not detected or fail
Yellow 🗌	DRAM is not detected or fail
White □	GPU is not detected or fail
Green	Booting device is not detected or fail


# **EZ Memory Detection LED**

This LED indicates that the memory module's power is not detected. If any memory module loses power, this LED will light up.




# JPWRLED1: LED power input

This connector is used by retailers to demonstrate the onboard LED lights.



# **EZ Digi-Debug LED**

The EZ Digi-Debug LED displays progress and error codes during and after POST. Refer to the EZ Digi-Debug LED table for details.



#### **Hexadecimal Character Table**

Hexadecimal	0	1	2	3	4	5	6	7
LED display	0	1	2	3	4	5	8	٦
Hexadecimal	8	9	А	В	С	D	Е	F
LED display	8	97	Œ	.0	E	TO	ш	F

### **Boot Phases**

Security (SEC) - initial low-level initialization

Pre-EFI Initialization (PEI) - memory initialization

Driver Execution Environment (DXE) - main hardware initialization

**Boot Device Selection (BDS)** – system setup, pre-OS user interface & selecting a bootable device (CD/DVD, HDD, USB, Network, Shell, ...)

# **EZ Digi-Debug LED Table**

# **SEC Progress Codes**

01	Power on. Reset type detection (soft/hard)
02	AP initialization before microcode loading
03	System Agent initialization before microcode loading
04	PCH initialization before microcode loading
06	Microcode loading
07	AP initialization after microcode loading
08	System Agent initialization after microcode loading
09	PCH initialization after microcode loading
0В	Cache initialization

#### **SEC Error Codes**

0C - 0D	Reserved for future AMI SEC error codes
0E	Microcode not found
0F	Microcode not loaded

# **PEI Progress Codes**

10	PEI Core is started

11	Pre-memory CPU initialization is started
12 - 14	Pre-memory CPU initialization (CPU module specific)
15	Pre-memory System Agent initialization is started
16 - 18	Pre-Memory System Agent initialization (System Agent module specific)
19	Pre-memory PCH initialization is started
1A - 1C	Pre-memory PCH initialization (PCH module specific)
2B	Memory initialization. Serial Presence Detect (SPD) data reading
2C	Memory initialization. Memory presence detection
2D	Memory initialization. Programming memory timing information
2E	Memory initialization. Configuring memory
2F	Memory initialization (other)
31	Memory Installed
32	CPU post-memory initialization is started
33	CPU post-memory initialization. Cache initialization
34	CPU post-memory initialization. Application Processor(s) (AP) initialization
35	CPU post-memory initialization. Boot Strap Processor (BSP) selection
36	CPU post-memory initialization. System Management Mode (SMM) initialization
37	Post-Memory System Agent initialization is started
38 - 3A	Post-Memory System Agent initialization (System Agent module specific)
3B	Post-Memory PCH initialization is started
3C - 3E	Post-Memory PCH initialization (PCH module specific)
4F	DXE IPL is started

# **PEI Progress Codes**

10	Memory not installed
----	----------------------

# **DXE Progress Codes**

60	DXE Core is started
61	NVRAM initialization
62	Installation of the PCH Runtime Services
63	CPU DXE initialization is started
64 - 67	CPU DXE initialization (CPU module specific)
68	PCI host bridge initialization
69	System Agent DXE initialization is started
6A	System Agent DXE SMM initialization is started

6B - 6F	System Agent DXE initialization (System Agent module specific)
70	PCH DXE initialization is started
71	PCH DXE SMM initialization is started
72	PCH devices initialization
73 - 77	PCH DXE Initialization (PCH module specific)
78	ACPI module initialization
79	CSM initialization
7A - 7F	Reserved for future AMI DXE codes
90	Boot Device Selection (BDS) phase is started
91	Driver connecting is started
92	PCI Bus initialization is started
93	PCI Bus Hot Plug Controller Initialization
94	PCI Bus Enumeration 32
95	PCI Bus Request Resources
96	PCI Bus Assign Resources
97	Console Output devices connect
98	Console input devices connect
99	Super IO Initialization
9A	USB initialization is started
9B	USB Reset
9C	USB Detect
9D	USB Enable
9E -9F	Reserved for future AMI codes
A0	IDE initialization is started
A1	IDE Reset
A2	IDE Detect
А3	IDE Enable
A4	SCSI initialization is started
A5	SCSI Reset
A6	SCSI Detect
A7	SCSI Enable
A8	Setup Verifying Password
A9	Start of Setup
AB	Setup Input Wait
AD	Ready To Boot event

AE	Legacy Boot event
AF	Exit Boot Services event
В0	Runtime Set Virtual Address MAP Begin
B1	Runtime Set Virtual Address MAP End
B2	Legacy Option ROM Initialization
В3	System Reset
B4	USB hot plug
B5	PCI bus hot plug
В6	Clean-up of NVRAM
В7	Configuration Reset (reset of NVRAM settings)
B8 - BF	Reserved for future AMI codes

# **DXE Error Codes**

D0	CPU initialization error
D1	System Agent initialization error
D2	PCH initialization error
D3	Some of the Architectural Protocols are not available
D4	PCI resource allocation error. Out of Resources
D5	No Space for Legacy Option ROM
D6	No Console Output Devices are found
D7	No Console Input Devices are found
D8	Invalid password
D9	Error loading Boot Option (LoadImage returned error)
DA	Boot Option is failed (StartImage returned error)
DB	Flash update is failed
DC	Reset protocol is not available

# S3 Resume Progress Codes

E0	S3 Resume is stared (S3 Resume PPI is called by the DXE IPL)
E1	S3 Boot Script execution
E2	Video repost
E3	OS S3 wake vector call
E4 - E7	Reserved for future AMI progress codes

# **S3** Resume Error Codes

E8	S3 Resume Failed
----	------------------

E9	S3 Resume PPI not Found
EA	S3 Resume Boot Script Error
EB	S3 OS Wake Error
EC - EF	Reserved for future AMI error codes

# **Recovery Progress Codes**

F0	Recovery condition triggered by firmware (Auto recovery)				
F1	Recovery condition triggered by user (Forced recovery)				
F2	Recovery process started				
F3	Recovery firmware image is found				
F4	Recovery firmware image is loaded				
F5 - F7	Reserved for future AMI progress codes				

# **Recovery Error Codes**

F8	Recovery PPI is not available			
F9	Recovery capsule is not found			
FA	Invalid recovery capsule			
FB - FF	Reserved for future AMI error codes			

### **ACPI States Codes**

The following codes appear after booting and the operating system into ACPI modes.

01	System is entering S1 sleep state
02	System is entering S2 sleep state
03	System is entering S3 sleep state
04	System is entering S4 sleep state
05	System is entering S5 sleep state
10	System is waking up from the S1 sleep state
20	System is waking up from the S2 sleep state
30	System is waking up from the S3 sleep state
40	System is waking up from the S4 sleep state
AC	System has transitioned into ACPI mode. Interrupt controller is in PIC mode.
AA	System has transitioned into ACPI mode. Interrupt controller is in APIC mode.

# **Installing OS, Drivers & MSI Center**

Please download and update the latest utilities and drivers at www.msi.com

# **Installing Windows 11**

- 1. Power on the computer.
- 2. Insert the Windows 11 installation disc/ USB into your computer.
- 3. Press the **Restart** button on the computer case.
- Press F11 key during the computer POST (Power-On Self Test) to get into Boot Menu.
- 5. Select the Windows 11 installation disc/USB from the Boot Menu.
- Press any key if screen shows Press any key to boot from CD or DVD... message. If not, please skip this step.
- 7. Follow the instructions on the screen to install Windows 11.

# **Installing Drivers with MSI Driver Utility Installer**




### Important

- Some new network chips have not been natively supported by Windows 11. It is recommended that the LAN driver be installed before installing drivers with MSI Driver Utility Installer. Please refer to www.msi.com to install the LAN driver for your motherboard.
- The MSI Driver Utility Installer will only pop up once. If you cancel or close it during the process, please refer to the Live Update chapter of the MSI Center manual to install the drivers. You can also go to www.msi.com to search your motherboard and download the drivers.
- MSI Driver Utility Installer needs to be installed over the internet.
- 1. Start up your computer in Windows 11.
- 2. Select Start > Settings > Windows Update, and then select Check for updates.
- 3. MSI Driver Utility Installer will pop up automatically.



 Select the I have read and agree to the MSI Terms of Use check box, and then click Next.



5. Check the **Select All** checkbox in the lower-left corner and click **Install** to install MSI Center and drivers. The installation progress will be shown at the bottom.



6. Once the progress has completed, click Finish.

### **MSI Center**

MSI Center is an application that helps you easily optimize game settings and smoothly use content creation softwares. It also allows you to control and synchronize LED light effects on PCs and other MSI products. With MSI Center, you can customize ideal modes, monitor system performance, and adjust fan speed.

#### **MSI Center User Guide**



If you would like to know more information about MSI Center, please refer to https://msi.gm/S391169E or scan the QR code to access.



# Important

Functions may vary depending on the product you have.

### **UFFI BIOS**

MSI UEFI BIOS is compatible with UEFI (Unified Extensible Firmware Interface) architecture. UEFI has many new functions and advantages that traditional BIOS cannot achieve, and it will completely replace BIOS in the future. The MSI UEFI BIOS uses UEFI as the default boot mode to take full advantage of the new chipset's capabilities. However, it still has a CSM (Compatibility Support Module) mode to be compatible with older devices. That allows you to replace legacy devices with UEFI compatible devices during the transition.



#### 

The term BIOS in this user guide refers to UEFI unless otherwise noted.

### **UEFI** advantages

- Fast booting UEFI can directly boot the operating system and save the BIOS self-test process. And also eliminates the time to switch to CSM mode during POST.
- Supports for hard drive partitions larger than 2 TB.
- Supports more than 4 primary partitions with a GUID Partition Table (GPT).
- Supports unlimited number of partitions.
- Supports full capabilities of new devices new devices may not provide backward compatibility.
- Supports secure startup UEFI can check the validity of the operating system to ensure that no malware tampers with the startup process.

### **Incompatible UEFI cases**

- 32-bit Windows operating system this motherboard supports only Windows 11 64-bit operating system.
- Older graphics card the system will detect your graphics card. If you use older graphics cards, it may display a warning message There is no GOP (Graphics Output protocol) support detected in this graphics card.



# !\ Important

We recommend that you replace it with a graphics card supporting GOP/UEFI or use CPU with integrated graphics for having normal function.

### **BIOS Setup**

The default settings offer the optimal performance for system stability in normal conditions. You should always keep the default settings to avoid possible system damage or failure booting unless you are familiar with BIOS.



### 🚹 Important

- BIOS items are continuously updated for better system performance. Therefore, the description may be slightly different from the latest BIOS and should be for reference only. You could also refer to the **HELP** information panel in BIOS.
- The BIOS screens, options and settings will vary depending on the products you have.

### **BIOS User Guide**



国際諸国 If you'd like to know more instructions on setting up the BIOS, please refer to https://msi.gm/S53FE767 or scan the QR code to access.



### \ Important

The appearance of the BIOS user guide may differ based on your motherboard model. Please consult your motherboard's BIOS for specific settings and options.

## **Entering BIOS Setup**

Press Delete key, when the Press DEL key to enter Setup Menu, F11 to enter Boot Menu message appears on the screen during the boot process.

### **Function key**

+/ -: Increase / decrease the value

**Enter**: Select the item

ESC: Exit

Tab: Next selection

Ctrl+F: Enter Search menu

F1: General Help list

**F2**: Add/ Remove a favorite item

**F3**: Enter Favorites menu

**F4**: Enter CPU core center & memory center information menu

**F5**: Enter Hardware Monitor menu

**F6**: Load optimized defaults


**F7**: Switch between Advanced mode and EZ mode

F8: Load Overclocking ProfileF9: Save Overclocking ProfileF10: Save Change and Reset\*

**F12**: Take a screenshot and save it to USB flash drive (FAT/ FAT32 format only).

#### How to find the BIOS version?

After entering the BIOS, find the BIOS version in the information box.



<sup>\*</sup> Pressing **F10** displays a confirmation message summarizing your changes. Select **Yes** or **No** to confirm.

## **Resetting BIOS**

If you encounter certain issues with your computer, restoring the default BIOS settings might help. You can reset the BIOS settings using the following methods:

- Enter the BIOS setup and press **F6** to load the optimized defaults.
- Use the Clear CMOS jumper on the motherboard to reset the BIOS.
- If your motherboard has a Clear CMOS button on the rear I/O panel, press it to reset the BIOS.



#### 

Ensure the computer is powered off before clearing the CMOS data. For more details, refer to the Clear CMOS jumper/button section in the manual.

### **Updating BIOS**

### **Updating BIOS with M-FLASH**

Before starting the M-Flash process, make sure you have:

• A USB flash drive with a capacity of 32GB or less that is formatted to FAT32.



# /!\ Important

M-Flash only supports FAT32 format, and the USB flash drive should not exceed 32GB.

A computer with internet access.

Please follow the steps below to update BIOS:

- 1. Download the latest BIOS file from the MSI website that matches your motherboard model, and save it to the USB flash drive.
- 2. If your motherboard has a Multi-BIOS switch, switch to the target BIOS ROM.
- 3. Insert the USB flash drive into your motherboard's USB port.
- 4. Enter flash mode by either:
  - Rebooting and pressing Ctrl + F5 during POST, then clicking Yes to reboot the
  - Rebooting and pressing Del during POST to enter BIOS, then clicking the M-FLASH button and clicking Yes to reboot.
- 5. Select a BIOS file from the M-FLASH File menu and press Enter.
- **6.** When prompted by a File Check message, click **Yes** to start the BIOS update.

Once the update reaches 100%, the system will reboot automatically.

### **Updating BIOS with MSI Center**

Before updating:

- Ensure the LAN driver is installed, and the internet connection is working properly.
- Close all other applications before updating the BIOS.

To update BIOS:

- 1. Install and launch MSI Center, then go to **Support** page.
- 2. Select Live Update and click on Advance button.
- 3. Select the BIOS file and click on Install button.
- 4. The installation reminder will appear, then click the **Install** button.

The system will automatically restart to update the BIOS. Once the flashing process is complete, the system will restart.


### **Updating BIOS with Flash BIOS Button**

- Download the latest BIOS file from the MSI website that matches your motherboard model.
- Rename the BIOS file to MSI.ROM, and save it to the root directory of a USB flash device.
- 3. Connect the power supply to CPU\_PWR1 and ATX\_PWR1. (You don't need to install the CPU and memory.)
- **4.** Plug the USB flash device with the **MSI.ROM** file into the **Flash BIOS Port** on the rear I/O panel.
- 5. Press the Flash BIOS Button to start flashing the BIOS. The LED will start flashing to indicate the process has begun.

The LED will turn off when the process is complete.

# **Block Diagram**

# **B850 MLG EDITION**



# **Regulatory Notices**

# **FCC-B Radio Frequency Interference Statement**



This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and radiates radio frequency energy, and, if not installed and used in

accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

#### NOTE

- The changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
- Shield interface cables and AC power cord, if any, must be used in order to comply with the emission limits.

### **FCC Conditions**

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- This device may not cause harmful interference.
- This device must accept any interference received, including interference that may cause undesired operation.

#### MSI Computer Corp.

901 Canada Court, City of Industry, CA 91748, USA (626)913-0828

www.msi.com

# **CE Conformity**

Products bearing the CE marking comply with one or more of the following EU Directives as may be applicable:

- RED 2014/53/EU
- Low Voltage Directive 2014/35/EU
- EMC Directive 2014/30/EU
- RoHS Directive 2011/65/EU
- Implementing measure Directive 2009/125/EC of ESPR Regulation (EU) 2024/1781

Compliance with these directives is assessed using applicable European Harmonized Standards.

The point of contact for regulatory matters is MSI-Europe: Eindhoven 5706 5692 ER Son, the Netherlands.

For any support regarding the EU General Product Safety Regulation (GPSR), please contact MSI Computer Europe B.V. via gpsr@msi.com Science Park Eindhoven 5706 5692 ER Son, the Netherlands

# **Products with Radio Functionality (EMF)**

This product incorporates a radio transmitting and receiving device. For computers in normal use, a separation distance of 20 cm ensures that radio frequency exposure levels comply with EU requirements. Products designed to be operated at closer proximities, such as tablet computers, comply with applicable EU requirements in typical operating positions. Products can be operated without maintaining a separation distance unless otherwise indicated in instructions specific to the product.

# **Restrictions for Products with Radio Functionality**



WLAN 5150-5350 MHz:

The WiFi operating in the band 5150-5350 MHz shall be restricted to indoor use in the European Union.

WLAN 6E:

a. Low Power Indoor (LPI) Wi-Fi 5.945-6.425 GHz devices:

The device is restricted to indoor use only when operating in the 5945 to 6425 MHz frequency range in the European Union.

b. Very Low Power (VLP) Wi-Fi 5.945-6.425 GHz devices (portable devices): The device is not permitted to be used on Unmanned Aircraft Systems (UAS) when operating in the 5945 to 6425 MHz frequency range in the European Union.



### Wireless Radio Use

This device is restricted to indoor use when operating in the 2.4GHz, 5GHz, 6GHz frequency band.

Cet appareil doit être utilisé à l'intérieur.

당해 무선설비는 운용중 전파혼신 가능성이 있음.

この製品は、周波数帯域 2.4GHz, 5GHz, 6GHz で動作しているときは、屋内においてのみ使用可能です。

#### NCC無線設備警告聲明

工作頻率2.4GHz, 5GHz, 6GHz該頻段限於室內使用。

經型式認證合格之低功率射頻電機,非經許可,公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。

低功率射頻電機之使用不得影響飛航安全及干擾合法通信;經發現有干擾現象時,應立即停用,並改善至無干擾時方得繼續使用。前項合法通信,指依電信法規定作業之無線電通信。低功率射頻電機須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

# Compliance Statement of Innovation, Science and Economic Development Canada (ISED)

This device complies with with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Operation in the band 5150-5250 MHz is only for indoor use to reduce the potential for harmful interference to co-channel mobile satellite systems.

CAN ICES-003(B)/NMB-003(B)

### **Australia and New Zealand notice**

This equipment incorporates a radio transmitting and receiving device. In normal use, a separation distance of 20 cm ensures that radio frequency exposure levels comply with the Australian and New Zealand Standards.

### クラスB情報技術装置

この装置は、クラスB情報技術装置です。この装置は、家庭環境で使用することを目的としていますが、この装置がラジオやテレビジョン受信機に近接して使用されると、受信障害を引き起こすことがあります。取扱説明書に従って正しい取り扱いをして下さい。

VCCI-B

### KC인증서

상호: (주)엠에스아이코리아 제품명: 메인보드

모델명: 30-7E62 제조년월: 2025년

R-R-MSI-30-7E62

제조자 및 제조국가: MSI/중국

# **Battery Information**

#### **European Union:**



Batteries, battery packs, and accumulators should not be disposed of as unsorted household waste. Please use the public collection system to return, recycle, or treat them in compliance with the local regulations.

#### BSMI:



#### 廢電池請回收

For better environmental protection, waste batteries should be collected separately for recycling or special disposal.

#### California, USA:



The button cell battery may contain perchlorate material and requires special handling when recycled or disposed of in California.

For further information please visit:

https://dtsc.ca.gov/perchlorate/

# **AWARNING**

- INGESTION HAZARD: This product contains a button cell or coin battery.
- **DEATH** or serious injury can occur if ingested.
- A swallowed button cell or coin battery can cause Internal Chemical Burns in as little as 2 hours.
- KEEP new and used batteries OUT OF REACH OF CHILDREN
- Seek immediate medical attention if a battery is suspected to be swallowed or inserted inside any part of the body.



- Remove and immediately recycle or dispose of used batteries according to local regulations and keep away from children. Do NOT dispose of batteries in household trash or incinerate.
- Even used batteries may cause severe injury or death. Call a local poison control center for treatment information.
- Battery type: CR2032
- Battery voltage: 3V
- Non-rechargeable batteries are not to be recharged.
- Do not force discharge, recharge, disassemble, heat above (manufacturer's specified temperature rating) or incinerate. Doing so may result in injury due to venting, leakage or explosion resulting in chemical burns.
- This product contains an irreplaceable battery.
- This icon indicates that a swallowed button battery can cause serious injury or death. Please keep batteries out of sight or reach of children.

### **Chemical Substances Information**

In compliance with chemical substances regulations, such as the EU REACH Regulation (Regulation EC No. 1907/2006 of the European Parliament and the Council), MSI provides the information of chemical substances in products at:

https://csr.msi.com/global/index

# **Environmental Policy**

- The product has been designed to enable proper reuse of parts and recycling and should not be thrown away at its end of life.
- Users should contact the local authorized point of collection for recycling and disposing of their end-of-life products.



- Visit the MSI website and locate a nearby distributor for further recycling information.
- Users may also reach us at gpcontdev@msi.com for information regarding proper Disposal, Take-back, Recycling, and Disassembly of MSI products.
- Please visit <a href="https://us.msi.com/page/recycling">https://us.msi.com/page/recycling</a> for information regarding the recycling of your product in the US.

# WEEE (Waste Electrical and Electronic Equipment) Statement



**European Union**: This symbol on the product indicates that this product cannot be discarded as municipal waste. Instead, it is your responsibility to dispose of your waste electrical and electronic equipment by handing it over to a designated collection point for recycling. For more information about where you can drop off your waste equipment for recycling, please contact your local city office, your household waste disposal service or the shop where you purchased the product.

### 日本JIS C 0950材質宣言

日本工業規格JIS C 0950により、2006年7月1日以降に販売される特定分野の電気および電子機器について、製造者による含有物質の表示が義務付けられます。

https://csr.msi.com/tw/Japan-JIS-C-0950-Material-Declarations

### **India RoHS**

This product complies with the "India E-waste (Management and Handling) Rule 2011" and prohibits use of lead, mercury, hexavalent chromium, polybrominated biphenyls or polybrominated diphenyl ethers in concentrations exceeding 0.1 weight % and 0.01 weight % for cadmium, except for the exemptions set in Schedule 2 of the Rule.

### Türkiye EEE yönetmeliği

Türkiye Cumhuriyeti: EEE Yönetmeliğine Uygundur

# Україна обмеження на наявність небезпечних речовин

Обладнання відповідає вимогам Технічного регламенту щодо обмеження

використання деяких небезпечних речовин в електричному та електронному обладнані, затвердженого постановою Кабінету Міністрів України від 3 грудня 2008 № 1057.

# Việt Nam RoHS

Kể từ ngày 01/12/2012, tất cả các sản phẩm do công ty MSI sản xuất tuân thủ Thông tư số 30/2011/TT-BCT quy định tạm thời về giới hạn hàm lượng cho phép của một số hóa chất độc hại có trong các sản phẩm điện, điện tử"

# MS-7E62主板产品中有害物质的名称及含量

				有害物质		
部件名称	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr(VI))	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
印刷电路板组件*	X	0	0	0	0	0
纽扣电池	0	0	0	0	0	0
外部信号连接头	X	0	0	0	0	0
其他 (例: 线材等)	X	0	0	0	0	0

- 本表格依据 SJ/T 11364 的规定编制。
- $\bigcirc$ : 表示该有害物质在该部件所有均质材料中的含量均在 GB/T 26572 规定的限量要求以下。
- ※: 表示该有害物质至少在该部件的某一均质材料中的含量超出 GB/T 26572 规定的限量要求,但所有部件都符合欧盟RoHS要求。
- \* 印刷电路板组件:包括印刷电路板及其构成的零部件。
- 上述有毒有害物质或元素清单会依型号之部件差异而有所增减。
- 产品部件本体上如有环保使用期限标识,以本体标识为主。

### 限用物質含有情況標示聲明書

設備名稱:電腦主	 幾板	型號(型式):MS-7E62					
	限用物質及其化學符號						
單元	鉛 (Pb)	汞 (Hg)	鎘 (Cd)	六價鉻 (Cr <sup>+6</sup> )	多溴聯苯 (PBB)	多溴二苯醚 (PBDE)	
電路板	0	0	0	0	0	0	
電子元件	_	0	0	0	0	0	
金屬機構件	_	0	0	0	0	0	
塑膠機構件	0	0	0	0	0	0	

備考1. "超出 $0.1\,\mathrm{wt}$  %" 及 "超出 $0.01\,\mathrm{wt}$  %" 係指限用物質之百分比含量超出百分比含量基準值。

備考2. "○" 係指該項限用物質之百分比含量未超出百分比含量基準值。

備考3. "─" 係指該項限用物質為排除項目。

# **Copyright and Trademarks Notice**





Copyright © Micro-Star Int' I Co., Ltd. All rights reserved. The MSI logo used is a registered trademark of Micro-Star Int' I Co., Ltd. All other marks and names mentioned may be trademarks of their respective owners. No warranty as to accuracy or completeness is expressed or implied. MSI reserves the right to make changes to this document without prior notice.



The terms HDMI™, HDMI™ High-Definition Multimedia Interface, HDMI™ Trade dress and the HDMI™ Logos are trademarks or registered trademarks of HDMI™ Licensing Administrator, Inc.

# **Technical Support**

If a problem arises with your system and no solution can be obtained from the user guide, please contact your place of purchase or local distributor. Alternatively, please try the following help resources for further guidance.

- Visit the MSI website for technical guide, BIOS updates, driver updates, and other information: http://www.msi.com
- Register your product at: http://register.msi.com

# **Revision History**

• Version 3.0, 2025/08, First release.

