

PX02-41X

规格: 66*100mm

用料: 105g书纸

表面: 无

印刷工艺:
四色印刷

说明书

修改

Power Bank PX02-41X 10000mAh / 45W
USER MANUAL →

Press to check the power level

Double click to turn on/off the built-in flashlight

Use a suitable USB port to charge the device

CONTACT US

✉ support@iniu.shop

☎ **+1 606-220-6170**
Hours: Mon-Fri, 9 AM - 6 PM (EST)

🌐 iniushop.com

📱 [@iniuofficial](#) [iniu_official](#)

[US] REP / Importer
FCC US Agent, LLC
3722 Illinois Avenue, Saint Charles, IL, 60174, USA
Telephone No: 708-571-3148
✉ Support@FCCUSAgent.com

Manufacturer: Shenzhen Topstar Industry Co., Ltd.
Address: Room 502, Building 20, South Fourth District, Zhangkeng Community, Minzhi Street, Longhua District, Shenzhen

SPECIFICATIONS

Model Number	PX02-41X
Cell Capacity	5000mAh × 2(10000mAh)
Battery Capacity	5000mAh/37Wh/7.4V
Rated Capacity	6200mAh(5V)
Battery Type	Lithium Battery
Size	4.36 × 2.75 × 0.65in / 110.8*69.8*16.6mm
Weight	6.65oz / 180.5g
Input	IN1/IN2: 5V ⇄ 3A 9V ⇄ 3A 12V ⇄ 2.25A 15V ⇄ 1.8A 27W(Max)
Output	OUT1/OUT2: 5V ⇄ 3A 9V ⇄ 3A 10V ⇄ 2.25A 12V ⇄ 3A 15V ⇄ 3A 45W(Max) OUT3: 5V ⇄ 3A 9V ⇄ 2A 10V ⇄ 2.25A 12V ⇄ 1.5A 22.5W(Max) OUT1+OUT2: 7.5W+7.5W=15W(Max) OUT1+OUT3: 7.5W+7.5W=15W(Max) OUT2+OUT3: 7.5W+7.5W=15W(Max) Total(OUT1+OUT2+OUT3): 5W+5W+5W=15W (Max)
Fast Charging Protocol	PD3.0, PD2.0, QC3.0, QC2.0, PPS, FCP, AFC, etc.
Limited Power Source	

Power allocation for each port is determined following a protocol handshake with the connected external device.

3 YEARS WARRANTY

LIFETIME TECHNICAL SUPPORT

FCC Warning:
This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
—Reorient or relocate the receiving antenna.
—Increase the separation between the equipment and receiver.
—Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
—Consult the dealer or an experienced radio/TV technician for help.

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

WARNINGS

Operating Conditions:
Ambient Operating Temperature: 10~40°C (50~104°F)
Storage & Transportation Temperature: -10~50°C (14~122°F)
Altitude: Not higher than 2000m (air pressure not lower than 80kPa)

IMPORTANT SAFETY INSTRUCTIONS
WARNING—When using this product, basic precautions should always be followed, including the following:
1. Read all instructions before using the product.
2. To reduce the risk of injury, close supervision is necessary when the product is used near children.
3. Do not insert fingers or hands into the product.
4. Do not expose the power bank to rain or snow.
5. Keep the product away from direct sunlight, fire, hot ovens, hot surfaces, or extremely low air pressure environments to prevent the risk of explosion, bulging, or leakage of flammable liquids or gases.
6. Avoid disassembling, crushing, puncturing, replacing batteries, dropping, or cutting the product to prevent fire, explosion, or leakage of flammable liquids or gases.
7. Do not place the product on a bed, under bedding, or in any airtight environment to prevent overheating, which may cause burns or deformation.
8. Using a non-manufacturer-approved power supply or charging cable may pose a risk of fire, explosion, or overheating.
9. Keep the product away from hazardous chemicals or cleaning agents. Do not immerse it in water or store it in a humid environment.
10. To maintain battery performance, charge and discharge the product at least once every three months.
11. If the product exhibits abnormal heat, deformation, swelling, or emits an unusual odor, stop using it immediately and contact a qualified recycling facility for proper disposal.
12. Do not use the power bank in excess of its output rating. Overloading outputs above the rated capacity may result in a risk of fire or injury.
13. Do not use a power bank that is damaged or modified. Damaged or modified batteries may exhibit unpredictable behavior, resulting in fire, explosion, or injury.
14. Do not disassemble the power bank. Refer servicing or repairs to qualified service personnel. Incorrect reassembly may result in a risk of fire or injury.
15. Do not expose a power bank to fire or excessive temperature. Exposure to fire or temperature above +40°C(+104°F) may cause explosion.
16. Servicing should be performed by qualified personnel using only identical replacement parts to ensure continued safety.
17. Switch off the power bank when not in use.

SAVE THESE INSTRUCTIONS

This product is equipped with an intelligent thermal management system. When the output power or temperature exceeds the predefined safety threshold, the device will automatically reduce its output power. This protective mechanism is in compliance with the IEC 62368-1 international safety standard.