



Noon Smart Lighting System

One Touch Lighting | Transforming Spaces



Through its advanced algorithms, Noon creates three pre-set lighting scenes each with a particular feel: Bright, Everyday, and Relax. [Sample text]



The Noon Lighting System coordinates your existing lights to create beautiful layered lighting for any room in your home. [Sample text]

The Noon Lighting System coordinates your existing lights to create beautiful layered lighting for any room in your home. Through its advanced algorithms, Noon creates three pre-set lighting scenes each with a particular feel: Bright, Everyday, and Relax. You can also create your own, based on how you use your room.



One-Touch

Change scenes using the Noon Room Director's touchscreen. Turn off all the lights in a room with one click.



Clean Light

Aligns the power with your type of bulb to eliminate the low-level popping, flickering and buzzing that can cause stress and agitation.



Night Light

Turns on ultra-low lighting, when motion is detected by the Room Director, to help guide you in the dark.



Vacation Mode

Learns to mimic your typical behavior. It appears as if you're home, even when you're not.



Control from anywhere

Control your Noon lighting from anywhere with your smartphone.



Voice Control

Control your lighting with your voice using popular intelligent personal assistants together with Noon.

SPECIFICATIONS

	ROOM DIRECTOR	EXTENSION SWITCH
Surface	High-Durability Curved Glass	Plastic
Color	Black	White
Screen	Touch-enabled 16-bit color AMOLED display 280 x 280 resolution at 277 pixel per inch (PPI) 1.45 in (3.68 cm) diagonal	—
Buttons	Mechanical click for lights on/off	Mechanical click for lights on/off Mechanical dimmer buttons
LED	—	Dimmer
Sensor	ToF motion sensor	—
Wireless	802.11b/g/n 2.4 GHz WiFi Bluetooth Low Energy	Bluetooth Low Energy
Size and Weight	Room Director Height: 3.2 in (82 mm) Width: 1.4 in (36 mm) Thickness: 0.8 in (19 mm) Weight: 1.62 oz (46 g) Dimming Base Height: 4.2 in (106 mm) Width: 1.8 in (44.5 mm) Thickness: 0.2 in (4 mm) Weight: 3.3 oz (94 g) Installed (Single-Gang Noon Wall Plate configuration) Height: 5.0 in (127.5 mm) Width: 3.2 in (81.5 mm) Thickness: 0.7 in (18.4 mm)	Extension Switch Height: 3.2 in (82 mm) Width: 1.4 in (36 mm) Thickness: 0.8 in (19 mm) Weight: 1.38 oz (39 g) Dimming Base Height: 4.2 in (106 mm) Width: 1.8 in (44.5 mm) Thickness: 0.2 in (4 mm) Weight: 3.3 oz (94 g) Installed (Single Gang Noon Wall Plate configuration) Height: 5.0 in (127.5 mm) Width: 3.2 in (81.5 mm) Thickness: 0.7 in (18.4 mm)
Power Consumption	Less than 1kWh/month, per switch	
Compatibility	Replaces light switches Works as single or multi-way switch Multi-way configurations for up to 4 switches per circuit; use all Noon switches Designed for indoor use only	
Not Compatible With	Switch-controlled power outlets Fans and light fixtures with built-in fans Appliances and non-lighting uses	
Compatible Bulb Types	Residential bulbs including: LED, Incandescent, Halogen, Fluorescent, and CFL bulbs Standard, MLV, and ELV light fixtures Dimmable and non-dimmable bulbs	
Power Requirements	Up to 650 watts (incandescent) For 2-, 3-, and 4-gang, up to 500 watts per switch	
Compatible Wiring	Neutral wire required Ground wire required 120V compatible (not for use with 240V circuits)	
Works With	Amazon Alexa	
Noon App	Noon app required for setup and remote control iOS devices require iOS 9 and above Android devices require Android 5.0 and above (with BLE)	
Scenes and Rooms	Up to 6 scenes per Room Director Up to X rooms per account	
Stand By Mode	When Power Toggle is in Off position, Room Director and Extension Switch behave as an on/off, non-dimming switch	
Battery	Rechargeable lithium-ion battery	
Warranty	1-year limited warranty For support, visit noonhome.com/support	
In the box	Room Director Base 4 Wire Connectors 2 Wall Screws Cleaning Cloth Wire labels Welcome Guide Installation Guide	Extension Switch Base 4 Wire Nuts 2 Wall Screws Wire labels Welcome Guide Installation Guide
Starter Kit Includes	Room Director 2 Extension Switches 3 Bases 3 Wall Plates (1,2, and 3-gang) 12 Wire Connectors 6 Wall Screws Cleaning Cloth Wire labels Welcome Guide Installation Guide	



INSTALL

If you have installed a light switch before, installing Noon will be easy.

- Please visit noonhome.com/install for directions and video
- If you'd rather have it professionally installed, we have Noon-certified installers on hand to help. Check out noonhome.com/installers
- Noon App available in the App Store and Android Market

WARRANTY

One year limited warranty.
Details at noonhome.com/warranty

INSTALL

Contact

- Website:
[Noonhome.com/support](https://noonhome.com/support)
- Phone:
General Consumer line:
+1 (844) 588-4626

Hours

- Weekdays:
7am - 7pm pacific
- Weekends:
7am - 5pm pacific



©2017 Noon Autem vel eum iriure dolor in hendrerit in vulputate velit esse molestie consequat, vel illum dolore eu feugiat nulla facilisis at vero eros et accumsan et iusto odio dignissim qui blandit praesent luptatum ril delentit augue duiis dolore tit nulla facilisi.

Lorem ipsum dolor sit amet, consectetur adipiscing elit, sed diam nonummy nibh euismod tincidunt ut laoreet dolore magna aliquam erat volutpat. At wisi enim ad minim veniam, quis nostrud exerci tation ullam corper suscipit lobortis nisl ut aliquip ex ea commodo conse quat horem ipsum dolor sit amet, conset ctetuer adipiscing elit, sed diam nonu mty nibh euism od tincidunt ut laoreet dolore magna aliquam erat volutpat. It wisi enim ad minim veniam, quis nostrud exerci tation ullamcorper suscipit lobortis nisl ut aliquip ex ea commodo consequat