



## **AX-SUB5RVC-6V**

### **Subaru (with 7" screen) 2015-up\***

\*Visit [AxxessInterfaces.com](http://AxxessInterfaces.com) for up-to-date vehicle specific applications.

#### **INTERFACE COMPONENTS**

- AX-SUB5RVC-6V • AX-CAM6V 12-volt to 6-volt converter

#### **APPLICATIONS**

<b>SUBARU</b>				
Crosstrek	2016	Impreza	2015-2016	
Forester	2015-2016	Outback	2015-2016	
		XV Crosstrek	2015	

#### **CONNECTIONS TO BE MADE**

- Connect the **Black** wire from the AX-SUB5RVC-6V, and the **Black** wire from the AX-CAM6V to chassis ground.
- Connect the **Red** wire labeled “Camera Power 6V” to the **Blue/Red** wire of the AX-CAM6V
- Connect the **Blue/White** wire from the AX-CAM6V to accessory power

#### **To the aftermarket radio:**

- Connect the **Yellow** RCA jack to the backup camera input.

**Note:** The reverse wire from the aftermarket radio must be connected to the vehicle's reverse wire in order to function properly.