

SEA65RGBS Wiring Instructions

STOP! BEFORE INSTALLATION-

If multiple speakers will be controlled with one remote, only remove battery shield from you plan on using. The remote will automatically pair with speakers when they power up for first time.

The included RF remote can control multiple speakers in one installations for ease of adjustment.



Fixed grill for easy installation Lighted RGB versions include on-board RGB controller with wireless remote

Powering the RGB lights

Connect a switched 12v and Grn to the master speaker



Connect the included RGB cable from master speaker to the second speaker



Remove the battery shield from the remote and you are ready to go

(Lights are wired in pairs, each pair runs of one master controller,

only 1 remote needed for multiple pairs of speakers)

