JUMPSMART™

JUMP STARTER · FLASHLIGHT · POWER BANK

User Manual

Table of Contents

Safety Information 1-3

Information de Sécurité 4-7

Introduction / What's Included 8

Components 9

Technical Specifications 10

Operation Instructions 11-20

- How to Charge JumpSmart 11-13
- How to Jump Start a Vehicle 14-16
- How to Use Flashlight 17-18
- How to Use the Power Bank 19-20

Certification 21

Limited Warranty 22-25

Copyright Notice 26

FCC Notice 27

Safety Information

SAFETY FIRST: To prevent potential product damage, property damage, personal injury, or even loss of life, **READ ALL** safety warnings and this user manual in its entirety before using the JumpSmart. By using the JumpSmart, you hereby agree that Limitless Innovations, Inc., an Illinois corporation and its affiliates ("Limitless") shall have no liability for any losses associated with property damage, personal injury or loss of life that are incurred by you or by any third party in connection with or relating in any manner whatsoever to your use of the JumpSmart. By using the JumpSmart, you hereby agree at all times to comply fully with all safety warnings, operating instructions and general safety information in this user manual. By using the JumpSmart, you further agree to hold harmless Limitless, (and Limitless' officers, directors, shareholders and employees) in connection with any losses sustained by you (including, without limitation, losses arising in whole or in part from property damage, personal injury or loss of life) relating in any manner whatsoever to your use of the JumpSmart.

IMPORTANT SAFETY INSTRUCTIONS

WARNING - When using this product, basic precautions should always be followed, including the following:

- Read all the instructions before using the product.
- To reduce the risk of injury, close supervision is necessary when the product is used near children.
- Do **NOT** put fingers or hands into the product.
- Use of an attachment not recommended or sold by Limitless Innovations may result in a risk of fire, electric shock, or injury to persons.
- To reduce the risk of product damage, always pull any cable from the plug, **NOT** the cord.
- Do **NOT** use a battery pack or appliance that is damaged or modified. Damaged or modified batteries may exhibit unpredictable behavior resulting in fire, explosion or risk of injury.
- Do **NOT** operate the JumpSmart with a damaged cord or plug, or a damaged output cable.
- Do **NOT** disassemble the JumpSmart, take it to a qualified service person when service or repair is required. Incorrect reassembly may result in a risk of fire or electric shock.
- To reduce the risk of electric shock, unplug the JumpSmart from the outlet before attempting any instructed servicing.
- **WARNING –** RISK OF EXPLOSIVE GASES.
- To reduce risk of battery explosion, follow these instructions and those published by Limitless Innovations and manufacturer of any equipment you intend to use in vicinity of the battery. Review cautionary marking on these products and on engine.

© Limitless Innovations, Inc.

SAFETY WARNINGS

- Misusing or incorrectly connecting your JumpSmart may cause electric shock to users, damage to the product, and/or damaged equipment.
- The JumpSmart and its accessories are **NOT** toys and should be kept away from children.
- Do **NOT** use any non-JumpSmart-branded accessories. Doing so may result in risk of fire, electric shock, and/or injury to person(s).
- Do **NOT** attempt to disassemble or repair the JumpSmart or its accessories.
- Do **NOT** attempt to replace the battery as it is a non-serviceable part.
- Do **NOT** twist the head of the JumpSmart. Doing so may damage the internal components.
- Do **NOT** drop the JumpSmart. Doing so may damage internal components otherwise not seen and must **NOT** be operated.
- Your JumpSmart may become warm during extended use. During operation, keep your JumpSmart away from materials that may be affected by these temperatures.
- Always charge JumpSmart in a well ventilated area.
- Do **NOT** insert any foreign objects into openings or ports of the JumpSmart.
- Always keep the main power switch in the **"OFF"** position when not in use to eliminate unnecessary battery power loss.
- Batteries should be recycled or disposed of, as per state and local guidelines.

© Limitless Innovations, Inc.

SAFETY PRECAUTIONS

- Have plenty of fresh water and soap nearby in case battery acid contacts skin, clothing, or eyes.
- Wear complete eye protection and clothing protection. Avoid touching eyes while working near battery.
- If battery acid contacts skin or clothing, wash immediately with soap and water. If acid enters eye, immediately flood eye with running cold water for at least 10 minutes and get medical attention immediately.
- **NEVER** smoke or allow a spark or flame in vicinity of battery or engine.
- Be extra cautious to reduce risk of dropping a metal tool onto battery. It might spark or short-circuit battery or other electrical part that may cause explosion.
- Under abusive conditions, liquid may be ejected from the battery; avoid contact. If contact accidentally occurs, flush with water. If liquid contacts eyes, additionally seek medical help. Liquid ejected from the battery may cause irritation or burns.
- Do **NOT** expose a power pack to fire or excessive temperature. Exposure to fire or temperature above 266°F may cause explosion.
- Have servicing performed by a qualified repair person using only identical replacement parts. This will ensure that the safety of the JumpSmart is maintained.

PLEASE SAVE THESE INSTRUCTIONS

© Limitless Innovations, Inc.

Information de Sécurité

TOUT D'ABORD, LA SÉCURITÉ: Afin de prévenir des dommages potentiels à la propriété ou au produit, des blessures corporelles ou la mort, **LISEZ TOUS** les avertissements de sécurité inscrites dans ce manuel de l'utilisateur avant d'utiliser le JumpSmart. Par l'utilisation du JumpSmart, vous acceptez que Limitless Innovations, inc., une entreprise de l'Illinois, et ses affiliés (« Limitless ») déclinent toute responsabilité quant aux pertes associées à des dégâts matériels, à des dommages corporels et à la mort causés par vous ou un tiers à la suite de l'utilisation du JumpSmart ou en rapport, de quelque façon que ce soit, avec votre utilisation du JumpSmart. En utilisant le JumpSmart, vous acceptez de vous conformer en tout temps à toutes les instructions de sécurité et d'utilisation, et aux consignes générales de sécurité inscrits dans ce manuel de l'utilisateur. En utilisant le JumpSmart, vous acceptez de dégager Limitless, ainsi que ses dirigeants, ses directeurs, ses actionnaires et ses employés, de toute responsabilité quant aux pertes subies (y compris, mais sans s'y limiter, les pertes engendrées en tout ou en partie, par des dommages à la propriété, des blessures ou la mort), relatives, de quelque manière que ce soit, à l'utilisation du JumpSmart.

© Limitless Innovations, Inc.

INSTRUCTIONS IMPORTANTES SUR LA SÉCURITÉ

AVERTISSEMENT: Lorsque vous utilisez ce produit, vous devriez prendre des précautions de base, y compris les suivantes:

- Lisez toutes les instructions avant d'utiliser le produit.
- Afin de réduire les risques de blessures, une surveillance étroite est de mise lorsque le produit est utilisé près d'enfants.
- Ne placez **PAS** vos doigts ou vos mains à l'intérieur du produit.
- L'utilisation d'un accessoire qui n'est pas recommandé ou vendu par le fabricant Limitless Innovations pourrait entraîner des risques d'incendie, de décharge électrique ou de blessures corporelles.
- Afin de réduire les risques de dommage à la fiche électrique et au cordon d'alimentation, débranchez le cordon du JumpSmart en maintenant la fiche plutôt que le cordon.
- N'utilisez **PAS** un bloc-piles ou un appareil endommagé ou modifié. Les batteries endommagées ou modifiées pourraient exhiber un comportement imprévisible occasionnant des incendies et des explosions ou des risques de blessures.
- Ne faites **PAS** fonctionner le JumpSmart ou un câble de sortie si sa fiche ou son cordon sont endommagés.
- Ne désassemblez **PAS** le JumpSmart; apportez-le à un technicien qualifié pour qu'il effectue les réparations ou la mise au point au besoin. Un mauvais réassemblage pourrait causer des incendies ou des décharges électriques.
- Afin de réduire les risques de décharges électriques, débranchez le JumpSmart de la prise électrique avant de tenter toute opération de dépannage.
- **AVERTISSEMENT -** RISQUES DE GAZ EXPLOSIFS.
- Afin de réduire les risques d'explosion de la batterie, suivez ces instructions et celles publiées par Limitless Innovation et le fabricant de l'équipement que vous tentez d'utiliser à proximité de la batterie. Consultez les avertissements indiqués sur ces produits et sur le moteur.

© Limitless Innovations, Inc.

AVERTISSEMENTS DE SÉCURITÉ

- Le mésusage ou la mauvaise connexion de votre JumpSmart pourraient entraîner des décharges électriques aux utilisateurs, des dommages au produit ou des dommages à l'équipement.
- Le JumpSmart et ses accessoires **NE** sont **PAS** des jouets et devraient être rangés hors de la portée des enfants.
- N'utilisez **PAS** d'accessoires autres que ceux du JumpSmart. L'utilisation d'accessoires autres pourrait causer des incendies, des décharges électriques ou des blessures.
- Ne tentez **PAS** de désassembler ou de réparer le JumpSmart ou ses accessoires.
- Ne tentez **PAS** de remplacer sa batterie, puisqu'il s'agit d'une pièce non réparable.
- Ne tournez **PAS** la tête du JumpSmart. Vous pourriez endommager des composants internes.
- Afin de réduire les risques d'endommager le produit, débranchez le cordon à partir de la fiche; **PAS** en tirant sur le cordon.
- N'échappez **PAS** le JumpSmart. Vous pourriez endommager des composants internes que vous ne pouvez pas voir. Si toutefois cela devait arriver, N'utilisez **PAS** l'appareil.
- Le JumpSmart pourrait chauffer lors d'une utilisation prolongée. Veuillez donc le garder à distance de tout matériau pouvant être affecté par la chaleur.
- Chargez toujours le JumpSmart dans un endroit bien aéré.
- N'insérez **PAS** d'objets étrangers dans les ouvertures ou les ports du JumpSmart.
- Maintenez toujours l'interrupteur en position d'arrêt lorsque l'appareil n'est pas utilisé afin de ne pas drainer la batterie inutilement.
- Les batteries devraient être recyclées ou jetées conformément aux directives locales ou de l'état.

© Limitless Innovations, Inc.

PRÉCAUTIONS DE SÉCURITÉ

- Ayez suffisamment d'eau fraîche et de savon à proximité au cas où de l'acide sulfurique entrerait en contact avec votre peau, vos vêtements ou vos yeux.
- Portez une protection oculaire complète et des vêtements de protection. Évitez de vous toucher les yeux lorsque vous travaillez à proximité de la batterie.
- Si de l'acide sulfurique entre en contact avec vos vêtements, nettoyez-les immédiatement avec de l'eau savonneuse. Si de l'acide entre en contact avec vos yeux, nettoyez-les immédiatement avec de l'eau froide pendant au moins 10 minutes et consultez un médecin sans tarder.
- Ne fumez **JAMAIS**, n'approchez ou ne créez **JAMAIS** de flamme ou d'étincelles près de la batterie ou du moteur.
- Soyez extrêmement prudent afin d'éviter tout risque de chute d'outil métallique sur la batterie. Cela pourrait étinceler ou court-circuiter la batterie ainsi que d'autres composants électriques et entraîner une explosion.
- Lorsque vous rechargez la batterie interne, travaillez dans un endroit bien aéré et ne bloquez pas la ventilation.
- En cas d'usage abusif, du liquide peut s'échapper des batteries; évitez donc d'y toucher. Si par mégarde vous y touchez, nettoyez la région avec de l'eau. Si le liquide entre en contact avec les yeux, consultez un médecin. Le liquide qui s'écoule de la batterie pourrait causer des irritations ou des brûlures.
- N'exposez **PAS** un bloc d'alimentation à une flamme ou à des températures extrêmes. L'exposition à une flamme ou à des températures au-dessus de 130°C pourraient causer une explosion.
- Demandez à un technicien qualifié d'effectuer l'entretien à l'aide de pièces de remplacement identiques. Ainsi, la sécurité du JumpSmart sera maintenue.
- Fixez les câbles de sortie à la batterie et au châssis. **NE** laissez **JAMAIS** les pinces de sortie se toucher.

VEUILLEZ CONSERVER CES INSTRUCTIONS

© Limitless Innovations, Inc.

Introduction

JUMPSMART | JUMP STARTER, FLASHLIGHT, AND POWER BANK
JumpSmart is the most practical vehicle jump starter on the market! Packed in a single, high-powered unit is a Vehicle Jump Starter, 4-Mode LED Flashlight, and Power Bank to use home or on-the-road to ensure peace of mind anywhere virtually anywhere.

WHAT'S INCLUDED
1x JumpSmart
1x Protective Sleeve
1x Smart Jumper Cables
1x Vehicle Charger
1x Wall Charger
1x Heavy-Duty Case
1x User Manual

© Limitless Innovations, Inc.

Components

The Smart Jumper Cables have 10 levels of protection listed below:

1. Reverse Polarity Protection
2. Short Circuit Protection
3. Over-Charge Protection
4. Over-Discharge Protection
5. Over-Temperature Protection
6. Timeout Protection
7. Vehicle Battery False Voltage Protection
8. Vehicle Engine Voltage Protection
9. Non-Sparking Full Protection
10. Low Input Voltage Protection

© Limitless Innovations, Inc.

Technical Specifications

Dimensions	2” x 2.5” x 8.5”
Weight	1.30 LBS
Battery Capacity	mAh 3300 x 3 / 37000 mWh
LED Flashlight Power	8W | 1250LX / 18FT | 330LM | 495FT Irradiation Distance
Jump Starter Capacity	Up to 8-Cyl Gas: 5.0L and Below / Diesel: 2.0L and Below
Battery Type	High-Grade Ratio Polymer Lithium Ion Battery
Input	DC 12-15V / 1A (Adapter Output 15VDC / 1A, Vehicle Charger 12VDC / 1A)
Self Consumption Current	< 150 uA
USB Port Output	5VDC / 2.4A
Jump Starter Port Output	Continuous output power (5s): 8V DC 115A (Lasted 5s) in labs environment instantaneous output power: 12V-8V DC 200A(Start)-400A(Peak), in genuine use
Working Temperature	-20°C - 60°C / -4°F - 140°F
Life Cycle	Approx. 1000 Times (After Then Decay 70%)

© Limitless Innovations, Inc.

HOW TO CHARGE JUMPSMART - SAFETY INFORMATION

SAFETY FIRST: To prevent potential product damage, property damage, personal injury, or even loss of life, **READ ALL** safety warnings located in the "Safety Information" section on page 1 of the user manual before attempting to operate the JumpSmart and its accessories.

DISCLAIMER / LIMITATION OF LIABILITY

By using the JumpSmart, you hereby agree that Limitless Innovations, Inc., an Illinois corporation and its affiliates ("Limitless") shall have no liability for any losses associated with property damage, personal injury or loss of life that are incurred by you or by any third party in connection with or relating in any manner whatsoever to your use of the JumpSmart. By using the JumpSmart, you hereby agree at all times to comply fully with all safety warnings, operating instructions and general safety information in this user manual. By using the JumpSmart, you further agree to hold harmless Limitless, (and Limitless' officers, directors, shareholders and employees) in connection with any losses sustained by you (including, without limitation, losses arising in whole or in part from property damage, personal injury or loss of life) relating in any manner whatsoever to your use of the JumpSmart.

© Limitless Innovations, Inc.

HOW TO CHARGE JUMPSMART

IN A HOME



1 Flip the Main Power Switch to the **OFF** position.

2 Plug the barrel connector end of the wall charger into the JumpSmart Charging Port Input located on the back panel of the JumpSmart.

3 Plug the Wall Adapter into a standard 110V AC wall outlet.



4 The battery is completely charged when all 4 Indicator Lights located on back panel of the JumpSmart are illuminated.

© Limitless Innovations, Inc.

HOW TO CHARGE JUMPSMART

IN A CAR



1 Flip the Main Power Switch to the **OFF** position.

2 Plug the barrel connector end of the Vehicle Charger into the JumpSmart Charging Port Input located on the back panel of the JumpSmart.

3 Plug the Vehicle Charger into a standard 12V DC receptacle.



4 The battery is completely charged when all 4 Indicator Lights located on back panel of the JumpSmart are illuminated.

© Limitless Innovations, Inc.

HOW TO JUMP START A VEHICLE - SAFETY INFORMATION

SAFETY FIRST: To prevent potential product damage, property damage, personal injury, or even loss of life, **READ ALL** safety warnings located in the "Safety Information" section on pages 1-3 before attempting to operate the JumpSmart and its accessories.

DISCLAIMER / LIMITATION OF LIABILITY
By using the JumpSmart, you hereby agree that Limitless Innovations, Inc., an Illinois corporation and its affiliates ("Limitless") shall have no liability for any losses associated with property damage, personal injury or loss of life that are incurred by you or by any third party in connection with or relating in any manner whatsoever to your use of the JumpSmart. By using the JumpSmart, you hereby agree at all times to comply fully with all safety warnings, operating instructions and general safety information in this user manual. By using the JumpSmart, you further agree to hold harmless Limitless, (and Limitless' officers, directors, shareholders and employees) in connection with any losses sustained by you (including, without limitation, losses arising in whole or in part from property damage, personal injury or loss of life) relating in any manner whatsoever to your use of the JumpSmart.

Risk of Explosion. This equipment has arcing or sparking parts which should not be exposed to flammable vapors. This equipment should be located at least 457 mm (18 inches) above the floor when used in a repair facility.

NOTE: This product is designed for a 12V / 200~400A vehicle battery. The total output of the JumpSmart Flashlight jump start feature is 12V and will adjust the current based on vehicle battery. This product is designed to jump start 8-cylinder gas engines up to 5.0L and 2.0L diesel engines and below. In the event that your vehicle is not starting, make sure everything is properly and securely connected. Wait a minimum of 60 seconds between each attempt and do not attempt more than 3 times. Contact a certified mechanic if your vehicle does not start after the third try. Every vehicle is different and therefore JumpSmart cannot guarantee every model or make of car is compatible.

© Limitless Innovations, Inc.

HOW TO JUMP START A VEHICLE

1 Prior to jumping a vehicle, locate the Main Power Switch on the back panel of the JumpSmart and flip to the **ON** position.



2 Plug the Smart Cable into the Jump Starter Port located on the back panel of the JumpSmart. Once plugged in the green and red Indicator Lights will flash in an alternating pattern on the Smart Cable.

3 Connect the **RED** clamp of the Smart Cable to the **POSITIVE** terminal of the vehicle battery.

NOTE: If the battery terminal is heavily corroded it may cause a bad connection, refer to the vehicles owner manual on how to clean.

4 Connect the **BLACK** clamp of the Smart Cable to the **NEGATIVE** terminal of the vehicle battery. Once both positive and negative clamps are properly connected, the green Indicator Light on the Smart Cable will remain illuminated. The jump start feature is now on standby.

NOTE: If the battery terminal is heavily corroded it may cause a bad connection, refer to the vehicles owner manual on how to clean.

5 Insert the key into the ignition and turn, or press the button to start the vehicle.

TIP: Connect the smart clamps to the terminal first while using Flashlight to see, then connect the Smart Cable to the JumpSmart as descibed in Step 2.

© Limitless Innovations, Inc.

HOW TO JUMP START A VEHICLE

6 If the vehicle does not start, wait at least 60 seconds before trying again

7 Do not attempt to jump start the vehicle more than 3 times.

8 Once the vehicle has been successfully started, disconnect the Smart Cable from the JumpSmart.

9 Remove the Smart Clamps in the reverse order they were connected.



10 Flip the Main Power Switch to the **OFF** position when not in use to eliminate unnecessary power loss.

© Limitless Innovations, Inc.

HOW TO USE FLASHLIGHT - SAFETY INFORMATION

SAFETY FIRST: To prevent potential product damage, property damage, personal injury, or even loss of life, **READ ALL** safety warnings located in the "Safety Information" section on page 1 of the user manual before attempting to operate the JumpSmart and its accessories.

DISCLAIMER / LIMITATION OF LIABILITY

By using the JumpSmart, you hereby agree that Limitless Innovations, Inc., an Illinois corporation and its affiliates ("Limitless") shall have no liability for any losses associated with property damage, personal injury or loss of life that are incurred by you or by any third party in connection with or relating in any manner whatsoever to your use of the JumpSmart. By using the JumpSmart, you hereby agree at all times to comply fully with all safety warnings, operating instructions and general safety information in this user manual. By using the JumpSmart, you further agree to hold harmless Limitless, (and Limitless' officers, directors, shareholders and employees) in connection with any losses sustained by you (including, without limitation, losses arising in whole or in part from property damage, personal injury or loss of life) relating in any manner whatsoever to your use of the JumpSmart.

© Limitless Innovations, Inc.

HOW TO USE FLASHLIGHT



1 Prior to using the LED flashlight, locate the Main Power Switch on the back panel of the JumpSmart and flip to the **ON** position.

2 Press and hold the LED Flashlight Power Button for 1 second to turn the flashlight **ON**. The flashlight is now in **HIGH BEAM MODE**.

3A Press and hold the LED Flashlight Power Button for 1 second again to turn the flashlight **OFF**.

OR

3B Click the button to cycle through the different modes:

- **LOW BEAM**
- **S.O.S.**
- **STROBE**
- **OFF**



4 Flip the Main Power Switch to the **OFF** position when not in use to eliminate unnecessary power loss.

© Limitless Innovations, Inc.

HOW TO USE THE POWER BANK - SAFETY INFORMATION

SAFETY FIRST: To prevent potential product damage, property damage, personal injury, or even loss of life, **READ ALL** safety warnings located in the "Safety Information" section on page 1 of the User Manual before attempting to operate the JumpSmart and its accessories.

DISCLAIMER / LIMITATION OF LIABILITY

By using the JumpSmart, you hereby agree that Limitless Innovations, Inc., an Illinois corporation and its affiliates ("Limitless") shall have no liability for any losses associated with property damage, personal injury or loss of life that are incurred by you or by any third party in connection with or relating in any manner whatsoever to your use of the JumpSmart. By using the JumpSmart, you hereby agree at all times to comply fully with all safety warnings, operating instructions and general safety information in this user manual. By using the JumpSmart, you further agree to hold harmless Limitless, (and Limitless' officers, directors, shareholders and employees) in connection with any losses sustained by you (including, without limitation, losses arising in whole or in part from property damage, personal injury or loss of life) relating in any manner whatsoever to your use of the JumpSmart.

© Limitless Innovations, Inc.

HOW TO USE THE POWER BANK



1 Prior to connecting any USB chargeable device, locate the Main Power switch on the back panel of the JumpSmart and flip to the **ON** position.

2 Connect the USB end to the USB Charging Port Located on the back panel of the JumpSmart.

3 Connect the opposite end to virtually any phone, tablet, or USB chargeable mobile device.



4 Flip the Main Power Switch to the **OFF** position when not in use to eliminate unnecessary power loss.

© Limitless Innovations, Inc.

Certification

UL WERCS

UL brings clarity and empowers trust to support the responsible design, production, marketing and purchase of the goods, solutions, and innovations of today and tomorrow. We connect people to safer, more secure, more sustainable products, services, experiences and environments – enabling smarter choices and better lives

ETL

JumpSmart is ETL certified to conform to ANSI/CAN/UL STD. 2743 and tested to comply with FCC Standard Part 15 for safety and reliability under the United States and Canadian standards.

Unauthorized changes or modifications to this device may impair the user's ability to operate this device and will void the warranty.

ETL AND FCC NOTICE TO USERS
Users are not permitted to make changes or modify this device or any of its companion products or components in any way. Changes or modifications are considered a safety hazard/risk and will void the warranty.

© Limitless Innovations, Inc.

Limited Warranty

Your use of the product shall at all times require you to comply with all terms, conditions of use, instructions and recommendations set forth within the JumpSmart and Terms and Conditions found at:

Manual: LimitlessInnovations.com/Manual/JumpSmart.pdf

Warranty Terms & Conditions:
LimitlessInnovations.com/Warranty-Terms-and-Conditions/JumpSmart

Are you having issues with your JumpSmart product?
Contact our support team today at:
LimitlessInnovations.com/Support or call us at (855) 843-4828

Subject to the exclusions contained below, Limitless Innovations, Inc. ("Limitless") warrants the JumpSmart product to be free from defects in materials and workmanship under normal consumer usage for a period of one (1) year from the date of original purchase, (the **"JumpSmart Limited Warranty"**). As utilized herein, the term "JumpSmart" (or the singular, JumpSmart product) shall include all products set forth above in the what's included section of this User Manual that may be sold by Limitless now or in the future. This JumpSmart Limited Warranty is a consumer's sole and exclusive remedy regarding any express warranty claim by a consumer and is subject to the exclusions on the following pages:

© Limitless Innovations, Inc.

Exclusions: The JumpSmart Limited Warranty shall not apply in the event of the occurrence of any of the following:

1. **Normal Wear and Tear.** The JumpSmart Limited Warranty shall not apply to cover the maintenance, repair and/or replacement of parts or the JumpSmart product due to normal wear and tear by the consumer.
2. **Abuse and Misuse.** The JumpSmart Limited Warranty shall not cover defects or damage that result in whole or in part from: (a) improper operation, storage, misuse or abuse, accident or neglect by the consumer (including, without limitation, physical damage, cracks and scratches to the surface of the JumpSmart product; (b) contact with liquid, water, rain, extreme humidity or heavy perspiration, sand, dirt or the like, extreme heat, or food; (c) use of the JumpSmart product for commercial purposes; (d) subjecting the JumpSmart product to abnormal usage or conditions; and/or (d) other acts which are not the sole and absolute fault of the JumpSmart.
3. **Unauthorized Service or Modification.** The JumpSmart Limited Warranty shall not cover defects or damages resulting in whole or in part from service, testing, adjustment, installation, maintenance, alteration, or modification in any way by someone other than the JumpSmart or its authorized service centers.
4. **Altered Products.** The JumpSmart Limited Warranty shall not cover defects or damages to a JumpSmart product with (a) serial numbers or date tags that have, at any time, been removed, altered, or obliterated; (b) broken seals or that show evidence or tampering; (c) mismatched board serial numbers; or (d) non-conforming or non-JumpSmart housings, or components.
5. **Communication Services.** Defects, damage, or the failure of the JumpSmart products due to any communication service or signal you may subscribe to or use with the JumpSmart product or software.

WHO IS COVERED?

This warranty extends only to the first consumer purchaser and is not transferable to any third party nor applicable to any subsequent owner other than the first consumer purchaser.

© Limitless Innovations, Inc.

HOW ARE CLAIMS RESOLVED?
If Limitless determines, in its sole and absolute discretion, that a claim is subject to the JumpSmart Limited Warranty, it will, at its sole option, repair or replace the JumpSmart product or alternatively, it will, in its discretion, refund the purchase price of any JumpSmart products or software. The JumpSmart product replacement will be with a functionally equivalent reconditioned / refurbished / pre-owned or new JumpSmart product or part.

For additional information, visit us at:
LimitlessInnovations.com/Support or call us at (855) 843-4828

WHO DO I CONTACT TO MAKE A CLAIM?
In the event of any warranty claim under the JumpSmart Limited Warranty, you can contact the telephone number below or provide a written correspondence to the address below at which time and in response thereto, you will receive instructions on how to ship any JumpSmart product at your expense, to a Limitless authorized repair center. To obtain service, you must include: (a) a copy of your receipt, bill of sale, or other comparable proof of purchase; (b) a written description of the problem; (c) the name if your service provider, if applicable; and (d) your mailing address, email address, and telephone number.

Mailing Address (Please call (855) 843-4828 first to obtain RMA #)
Limitless Innovations | 4800 Metalmaster Way | McHenry, IL 60050

WHAT OTHER LIMITATIONS ARE THERE?
ANY WARRANTY CLAIM SHALL BE LIMITED TO LIMITLESS COST OF MATERIAL ON THE JUMPSMART PRODUCT DETERMINED TO HAVE A MANUFACTURER'S DEFECT. IN NO EVENT SHALL LIMITLESS BE LIABLE TO ANY PARTY FOR ANY LABOR COSTS OR ANY OTHER DIRECT, INDIRECT, CONSEQUENTIAL, INCIDENTAL OR SPECIAL DAMAGES, WHETHER IN CONTRACT OR TORT AND LIMITLESS EXPRESSLY DISCLAIMS LIABILITY FOR ANY DAMAGES OF ANY KIND ARISING UNDER ANY THEORY OF LAW WHATSOEVER. THE PERFORMANCE OF THE JUMPSMART PRODUCT DEPENDS ON THE PURCHASER'S ADHERENCE TO MANUFACTURER PRODUCT INSTRUCTIONS AND LIMITLESS WILL NOT BE RESPONSIBLE TO PURCHASER FOR ANY DEVIATIONS

© Limitless Innovations, Inc.

THEREFROM. SOME STATES DO NOT ALLOW THE EXCLUSION OR LIMITATION OF INCIDENTAL OR CONSEQUENTIAL DAMAGES, SO THE ABOVE LIMITATION OR EXCLUSION REGARDING INCIDENTAL OR CONSEQUENTIAL DAMAGES MAY NOT APPLY TO YOU. ALL IMPLIED WARRANTIES, INCLUDING, WITHOUT LIMITATION, THE IMPLIED WARRANTY OF MERCHANTABILITY AND THE IMPLIED WARRANTY OF FITNESS FOR A PARTICULAR PURPOSE SHALL EXPIRE ON THE DATE WHICH IS 1 YEAR FROM THE DATE OF FIRST PURCHASE OF THE JUMPSMART PRODUCT BY THE CONSUMER. SOME STATES DO NOT ALLOW LIMITATIONS ON HOW LONG AN IMPLIED WARRANTY LASTS, SO THE ABOVE LIMITATION MAY NOT APPLY TO YOU. WITH RESPECT TO THAT PERIOD OF TIME BEYOND THE JUMPSMART 1 YEAR LIMITED WARRANTY PERIOD, LIMITLESS DISCLAIMS AND FURTHER MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO, ANY WARRANTY OF MERCHANTABILITY OR WARRANTY OF FITNESS FOR A PARTICULAR PURPOSE. PLEASE NOTE THIS JUMPSMART LIMITED WARRANTY GIVES YOU SPECIFIC LEGAL RIGHT, AND YOU MAY ALSO HAVE OTHER RIGHTS WHICH VARY FROM STATE TO STATE.

NATIONAL STATUTORY RIGHTS

CONSUMERS IN SOME JURISDICTIONS MAY HAVE LEGAL RIGHTS UNDER APPLICABLE NATIONAL LEGISLATION GOVERNING THE SALE OF CONSUMER GOODS, INCLUDING, WITHOUT LIMITATION, NATIONAL LAWS IMPLEMENTING EC DIRECTIVE 99/44. THESE RIGHTS ARE NOT AFFECTED BY THE WARRANTIES IN THIS LIMITED WARRANTY.

© Limitless Innovations, Inc.

Copyright Notice

All of the JumpSmart products and information shared in this manual are protected by copyright. Copying, reproducing, reverse engineering or distributing any information of the JumpSmart related products hardware or software without a formal and written authorization and license from Limitless Innovations, Inc. is prohibited and may result in legal action to the full extent of the law.

© Limitless Innovations, Inc.

FCC Notice

"This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation."

"WARNING: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment."

"NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications."

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. Consult the dealer or an experienced radio/TV technician for help.

© Limitless Innovations, Inc.

JUMPSMART™

JUMP STARTER · FLASHLIGHT · POWER BANK

All rights reserved. JumpSmart is a trademark of Limitless Innovations, Inc. Design and specifications subject to change without notice. All other trademarks included herein are property of their respective owners. Cable adapters sold separately. Electronic devices and automobiles not included.

Made in China

Phone: (855) 843-4828

Email: Support@LimitlessInnovations.com

Website: LimitlessInnovations.com

© Limitless Innovations, Inc.