



HP Neverstop Laser MFP 1202w

Wireless, high-capacity toner tank that scans and saves you up to 60% on toner^{1,5}

Exceptional value right out of the box – up to 60% savings on toner¹ with 5000 pages of toner included.² Easily restore toner levels with a 15-second, mess-free experience.³ Print and scan virtually anywhere with HP Smart app.⁴



Print Speed: Letter: Up to 21 ppm black
First Page Out: As fast as 8.5 sec black
Print Resolution: Black (best): Up to 600 x 600 x 2 dpi
Standard Connectivity: Hi-Speed USB 2.0 port; Built-in WiFi
 802.11b/n/g
Mobile Printing Capability: Apple AirPrint™; Google Cloud Print™; HP Smart App; Mopria™ Certified; Wi-Fi® Direct Printing
Duty cycle: Monthly (letter): Up to 20,000 pages
Display: ICON LCD
Paper Handling: 150-sheet input tray; 100-sheet output bin



Up to 60% savings on toner every time you reload

- Count on toner savings right out of the box.¹ Get up to 60% savings on toner every time you reload.¹
- Get 5000 pages of toner right out of the box² – up to 7x more pages than in class HP lasers.⁶
- Breeze through tasks with versatile MFP performance – print, scan, and copy.
- Business doesn't need to wait for your printer. Help maximize your uptime with fast print speeds.

15-second, mess-free reloadable toner

- Get a mess-free experience,³ and easily restore toner levels with the toner reload kit.⁷
- This innovative laser printer delivers exceptional quality, page after page.
- Produce sharp text and bold blacks for high-quality, black-and-white documents.
- HP Neverstop with Original HP Toner Reload Kit meets ecolabel requirements: ENERGY STAR 3.0 and BLUE ANGEL.

Save time printing from virtually anywhere

- Print, scan, and copy virtually anywhere, and receive notifications on your phone, with HP Smart app.⁴
- Easily share resources – access and print with wireless networking.⁵
- Connect your mobile device directly to your printer – and easily print without accessing a network.⁹
- Save time and eliminate steps in repetitive tasks with customizable shortcuts, using Smart Tasks.⁴

¹Based on internal HP comparison of MSRP and cost-per-page of in-class HP LaserJet Pro M15 and HP LaserJet Pro MFP M28 with standard-fill HP 44A/48A Black Original LaserJet Toner Cartridge, as of July 2019. For details see <http://www.hp.com/go/learnaboutsupplies> ²Actual yield varies considerably based on content of printed pages and other factors. Average based on ISO/IEC 19752 and continuous printing. For details see <http://www.hp.com/go/learnaboutsupplies> ³HP internal research and Keypoint Intelligence-Buyers Lab 2018 study commissioned by HP. For details see <http://www.keypointintelligence.com/HPNeverstop> ⁴Requires the HP Smart app download. For details on local printing requirements see <http://www.hp.com/go/mobileprinting>. Certain features/software are available in English language only. ⁵Wireless operations are compatible with 2.4 GHz operations only. Learn more at <http://www.hp.com/go/mobileprinting> ⁶Based on HP LaserJet Pro M15 and HP LaserJet Pro MFP M28 with standard-fill HP 44A/48A Black Original LaserJet Toner Cartridge with ISO yield of 500 pages. Actual yield varies considerably based on content of printed pages and other factors. Average based on ISO/IEC 19752 and continuous printing. For details see <http://www.hp.com/go/learnaboutsupplies> ⁷Toner reload kit is not included with the printer; please purchase separately. ⁸Compared to majority of OEM mobile printing apps for inkjet & laser printers & all-in-ones for home & home office, priced less than or equal to \$429.99 USD. Market share as reported by IDC Q4 2018 Hardcopy Peripherals Tracker. Claim based on lab testing and research of printer manufacturer's mobile print apps and Keypoint Intelligence-Buyers Lab study commissioned by HP. See Sept 2018 report at <http://www.keypointintelligence.com/HPSmartApp> ⁹Mobile device needs to be connected to Wi-Fi Direct® signal of a Wi-Fi Direct-supported AIO or printer prior to printing. Details at <http://www.hp.com/go/mobileprinting>. Wi-Fi Direct® is a registered trademark of Wi-Fi Alliance®.

HP Neverstop Laser MFP 1202w Technical specifications

Functions / Multitasking supported	Print, copy, scan / Yes
Print speed black	Letter: Up to 21 ppm; First page out: As fast as 8.5 sec
Print resolution	Black (best): Up to 600 x 600 x 2 dpi; Black (fine lines): Up to 600 x 600 dpi
Print technology	Laser
Print resolution technologies	HP FastRes 1200 (600 x 600 x 2 dpi)
Print cartridges number	1 Imaging Drum
Standard print languages	PCLmS; URF; PWG
Printer smart software features	Apple AirPrint™, Mopria-certified, HP Auto-On/Auto-Off, Wi-Fi Direct, HP Smart App, HP Smart Task
Scan type / Technology	Flatbed / D-CIS
Scan resolution	Hardware: Up to 600 ppi; Optical: Up to 600 ppi
Scan file format	JPG, RAW (BMP), PNG, TIFF, PDF
Scan size maximum	Flatbed: 8.5 x 11.7 in
Scanner advanced features	No
Bit depth / Grayscale levels	24-bit/256
Copy resolution	Black (text and graphics): Up to 600 x 600 dpi (flatbed)
Maximum number of copies	Up to 99 copies
Copier settings	Number of Copies; Lighter/Darker; Optimize; Paper
Copier resize	25 to 400%
Standard connectivity	Hi-Speed USB 2.0 port; Built-in WiFi 802.11b/n/g
Wireless capability	Yes, Wireless Wi-Fi Direct, Hi-speed USB
Mobile printing capability	Apple AirPrint™; Google Cloud Print™; HP Smart App; Mopria™ Certified; Wi-Fi® Direct Printing
Memory	Standard: 64 MB; Maximum: 64 MB
Processor speed	500 MHz / Hard disk: None
Duty cycle	Monthly letter: Up to 20,000 pages
Recommended monthly page volume	250 to 2500
Media types supported	Plain paper, Heavy paper, Bond paper, Label, Light paper, Envelope
Media weight supported	14 to 27 lb
Media sizes supported	Letter; envelopes (No.10); custom
Media Sizes Custom	4.13 x 5.85 to 8.5 x 14
Paper handling	Input Capacities: Up to 150 sheets Standard ; Up to 1 envelope Output Capacities: Up to 100 sheets Standard Duplex Options: Manual (driver support provided) Standard paper trays: 1 input tray

What's in the box	5HG92A HP Neverstop laser1200w Printer; Preinstalled HP Black Original Imaging Drum (~5000 pages yield); Reference guide; Setup guide; Regulatory flyer; Support flyer; Warranty guide; Power cord; USB cable
Replacement cartridges ³	HP 143A Black Original Neverstop Laser Toner Reload Kit (Yield ~2500 pages); HP 143AD Dual pack Black Original Neverstop Laser Toner Reload Kit (Yield ~2x2500 pages). Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies
Product dimensions	W x d x h: 14.98 x 11.55 x 11.3 in; Maximum: 14.98 x 15.16 x 20.51 in
Product weight	19.25 lb
Warranty features	HP one year hardware limited warranty. For full terms and conditions, visit: http://www.hp.com/go/orderdocuments .
Energy efficiency compliance	ENERGY STAR 3.0 Certified, BLUE ANGEL Certified
Control panel	ICON LCD
Display description	ICON LCD
Software included	For Windows OS: HP Software Installer, HP Software Uninstaller (exclude Win8+), HP PCLmS Printer Driver, HP Device Experience (DXP), HP Web Services Assist (HP Connected), Device Setup & Software, Online user manuals, HP Printer Assistant, HP Scan Driver, HP Scan Application, HP Product Improvement Study. For Mac OS: Welcome Screen, (Directs users to HP.com or OS App Source for LaserJet Software)
Compatible operating systems	Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer. Apple® OS X El Capitan (v10.11) macOS Sierra (v10.12) macOS High Sierra, (v10.13); 1.5 GB HD; Internet required; USB Linux (For more information, see https://developers.hp.com/hp-linux-imaging-and-printing)
Compatible network operating systems	Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer. Apple® OS X El Capitan (v10.11) macOS Sierra (v10.12) macOS High Sierra, (v10.13); 1.5 GB HD; Internet required; USB Linux (For more information, see https://developers.hp.com/hp-linux-imaging-and-printing)
Minimum system requirements	PC: Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer.; Mac: Apple® OS X El Capitan (v10.11) macOS Sierra (v10.12) macOS High Sierra, (v10.13); 1.5 GB HD; Internet required; USB
Power ²	Power supply type: Internal (Built-in) power supply; Power requirements: 110V - 127V nominal @ +/-10% (min 99V, max 140V), 50 - 60Hz nominal +/- 3Hz (min 47Hz, max 63Hz); Power consumption: 338 watts (Active Printing), 3.3 watts (Ready), 0.95 watts (Sleep), 0.1 watts (Manual off)
Acoustics	Acoustic power emissions: 6.5 B(A); Acoustic pressure emissions: 51 dB(A)
Operating environment	Operating temperature range: 15 to 32.5°C; Recommended operating temperature: 17.5 to 25°C; Storage temperature range: -20 to 50°C; ; Operating humidity range: 10 to 80% RH; Recommended humidity operating range: 30 to 70% RH
HP Service and Support options	UC4X6E - HP 1y Onsite Exchange NS L 1xxx MFP SVC; UB4X8E - HP 2y Onsite Exchange NS L 1xxx MFP SVC; UB4X9E - HP 3y Onsite Exchange NS L 1xxx MFP SVC; UB4Y0E - HP 4y Onsite Exchange NS L 1xxx MFP SVC; UC4X7E - HP 5y Onsite Exchange NS L 1xxx MFP SVC; UB4Y1E - HP 2y NBD Exchange NS L 1xxx MFP SVC; UB4Y2E - HP 3y NBD Exchange NS L 1xxx MFP SVC; UB4Y3E - HP 4y NBD Exchange NS L 1xxx MFP SVC; UB4Y4E - HP 2y Std Exchange NS L 1xxx MFP SVC; UB4Y5E - HP 3y Std Exchange NS L 1xxx MFP SVC; UB4Y6E - HP 4y Std Exchange NS L 1xxx MFP SVC; UB4Y7E - HP 2y Return to Depot NS L 1xxx MFP SVC; UB4Y8E - HP 3y Return to Depot NS L 1xxx MFP SVC; UB4Y9E - HP 4y Return to Depot NS L 1xxx MFP SVC

Learn more at
<http://www.hp.com>

¹ HP Black Original Laser Imaging Drum (introductory ~5,000 page black toner yield provided, with ~20,000 page Imaging Drum useful life). Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies> ² Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typically based on measurement of 115 V device. ³ Declared black toner page yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>. HP W1103A and HP W1104A replacement supplies are not imported, sold, nor warrantied in China. ⁴ Declared black toner page yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>. HP W1103A and HP W1104A replacement supplies are not imported, sold, nor warrantied in China. ⁵ HP SureSupply alerts you when your Imaging Drum is running low and helps you purchase online or locally through HP or a participating retailer. Only available with Original HP supplies; Internet access required. To learn more, visit <http://www.hp.com/go/SureSupply> ⁶ Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115 V device.

