

User Guide

UD-3900Z

Getting Started on Windows

1. Download and install the [DisplayLink software](#).
2. Connect the power supply to your wall socket or power strip, and then to the docking station.
3. Connect the display(s) to the HDMI ports on the rear of the docking station.
4. Connect the provided USB-C or USB 3.0 cable to the USB-B port on the rear of the docking station, and the other end into your computer's USB-C or USB 3.0 port.

Getting Started on macOS

1. Download and install the [DisplayLink Manager for macOS](#).
2. Detailed installation and configuration instructions can be found by clicking on the "INFO" button, or in the next step.
3. Please follow the detailed instructions below to install and configure the DisplayLink software for your version of macOS:
 - [macOS 13 and above](#)
 - [macOS 11 or 12](#)
4. Connect the power supply to your wall socket or power strip, and then to the docking station.
5. Connect the display(s) to the HDMI ports on the rear of the docking station.
6. Connect the provided USB-C or USB 3.0 cable to the USB-B port on the rear of the docking station, and the other end into your computer's USB-C or USB 3.0 port.

Getting Started on ChromeOS

1. No driver download is necessary, though ChromeOS version 100 or later is required.
2. Connect the power supply to your wall socket or power strip, and then to the docking station.
3. Connect the display(s) to the HDMI ports on the rear of the docking station.
4. Connect the provided USB-C or USB 3.0 cable to the USB-B port on the rear of the docking station, and the other end into your computer's USB-C or USB 3.0 port.

Compatibility

Laptop Requirements

UD-3900Z can be used with laptops equipped with USB 3.0 or USB-C ports supporting at least 5Gbps data transfer.

Supported Operating Systems

Windows 10 & 11, macOS 11+, ChromeOS 100+

Monitor Compatibility

UD-3900Z supports up to two monitors connected via HDMI. It supports resolutions up to 1920x1200 60Hz on each monitor.

UD-3900Z is ready to be used with HDMI-equipped monitors, but DVI and VGA monitors can also work through the use of video adapters (sold separately).

DisplayPort monitors are not supported.

Looking for more information? Additional information for getting started and product details are available on the Plugable product page: <https://plugable.com/ud-3900z/#nav-get-started>