Datasheet

HP Neverstop Laser 1001nw

Wireless, high-capacity toner tank that saves you up to 60% on toner [1,5]

Exceptional value right out of the box – up to 60% savings on toner[1] with 5000 pages of toner included.[2] Easily restore toner levels with a 15-second, mess-free experience.[3] Print and scan virtually anywhere with HP Smart app.[4]

Print Speed: Letter: Up to 21 ppm black
First Page Out: As fast as 8.5 sec black
Print Resolution: Black (best): Up to 600 x 600 x 2 dpi
Standard Connectivity: Hi-Speed USB 2.0 port; Built-in WiFi 802.11b/n/g; Fast Ethernet 10/100 Base
Mobile Printing Capability: Apple AirPrint™; Google Cloud Print™; HP Smart App and other mobile Apps; Wi-Fi® Direct printing; Mopria™-certified
Duty cycle: Monthly (letter): Up to 20,000 pages
Display: LED
Paper Handling: 150-sheet input tray; 100-sheet output bin

Up to 60% savings on toner every time you reload[1]

- Count on toner savings right out of the box.[1] Get up to 60% savings on toner every time you reload.[1]
- Get 5000 pages of toner right out of the box[2] – up to 7x more pages than in-class HP lasers.[6]
- Business doesn't need to wait for your printer. Help maximize your uptime with fast print speeds.
- Start printing right away. The intuitive control panel helps you complete projects quickly and easily.

15-second, mess-free reloadable toner[3]

- Get a mess-free experience,[3] and easily restore toner levels with the toner reload kit.[7]
- This innovative laser printer delivers exceptional quality, page after page.
- Produce sharp text and bold blacks for high-quality, black-and-white documents.
- HP Neverstop with Original HP Toner Reload Kit meets ecolabel requirements: ENERGY STAR 3.0 and BLUE ANGEL.

Save time printing from virtually anywhere[4]

- Print and copy virtually anywhere, and receive notifications on your phone, with HP Smart app.[4]
- Easily share resources – access and print with wireless and Ethernet networking.[5]
- Connect your mobile device directly to your printer – and easily print without accessing a network.[9]
- Save time and eliminate steps in repetitive tasks with customizable shortcuts, using Smart Tasks.[4]

HP Neverstop Laser 1001nw Technical specifications

Functions / Multitasking supported	Print / No
Print speed black	**Letter:** Up to 21 ppm; **First page out:** As fast as 8.5 sec
Print resolution	**Black (best):** Up to 600 x 600 x 2 dpi; **Black (fine lines):** Up to 600 x 600 dpi
Print technology	Laser
Print resolution technologies	600 x 600 dpi
Print cartridges number	1 Imaging Drum
Standard print languages	PCLmS; URF; PWG
Printer smart software features	Apple AirPrint™, Mopria-certified, HP Auto-On/Auto-Off, Wi-Fi Direct, HP Smart App, HP Smart Task
Standard connectivity	Hi-Speed USB 2.0 port; Built-in WiFi 802.11b/n/g; Fast Ethernet 10/100 Base
Network capabilities	10/100/1000 Base-TX Networking and Wifi 802.11 b/g/n
Wireless capability	Yes, Wireless Wi-Fi Direct, built-in fast Ethernet, Hi-speed USB
Mobile printing capability[7]	Apple AirPrint™; Google Cloud Print™; HP Smart App and other mobile Apps; Wi-Fi® Direct printing; Mopria™-certified
Memory	**Standard:** 32 MB; **Maximum:** 32 MB
Processor speed	500 MHZ
Duty cycle[8]	Monthly letter: Up to 20,000 pages
Recommended monthly page volume[9]	250-2500
Media types supported	Plain paper, Heavy paper, Bond paper, Label, Light paper, Envelope
Media weight supported	14 to 27 lb
Media sizes supported	Letter; envelopes (No.10); custom
Media Sizes Custom	4.13 x 5.85 to 8.5 x 14
Paper handling	**Input Capacities:** Up to 150 sheets Standard **Output Capacities:** Up to 100 sheets Standard **Duplex Options:** Manual (driver support provided) **Standard paper trays:** 1 input tray

What's in the box	**5HG80A** HP Neverstop Laser M1000w Printer; Preinstalled HP Black Original Imaging Drum (~5000 pages yield); Reference guide; Setup guide; Regulatory flyer; Support flyer; Warranty guide; Power cord; USB cable
Replacement cartridges[6]	HP 143A Black Original Neverstop Laser Toner Reload Kit (Yield ~2500 pages); HP 143AD Dual pack Black Original Neverstop Laser Toner Reload Kit(Yield ~2x2500 pages)
Product dimensions	**W x d x h:** 14.98 x 14.63 x 8.31 in; **Maximum:** 14.98 x 18.31 x 17.52 in
Product weight[3]	15.43 lb
Warranty features	HP one year hardware limited warranty. For full terms and conditions, visit: www.hp.com/go/orderdocuments.
Energy efficiency compliance	ENERGY STAR 3.0 Certified, BLUE ANGEL Certified
Control panel	LED
Display description	LED
Software included	For Windows OS: HP Software Installer, HP Software Uninstaller (exclude Win8+), HP PCLmS Printer Driver, HP Device Experience (DXP), HP Web Services Assist (HP Connected), Device Setup & Software, Online user manuals, HP Printer Assistant, HP Product Improvement Study. For Mac OS: Welcome Screen, (Directs users to HP.com or OS App Soure for LaserJet Software)
Compatible operating systems[11]	Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer. Apple®OS X El Capitan (v10.11) macOS Sierra (v10.12) macOS High Sierra, (v10.13); 1.5 GB HD; Internet required; USB Linux (For more information, see https://developers.hp.com/hp-linux-imaging-and-printing)
Compatible network operating systems	Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer. Apple®OS X El Capitan (v10.11) macOS Sierra (v10.12) macOS High Sierra, (v10.13); 1.5 GB HD; Internet required; USB Linux (For more information, see https://developers.hp.com/hp-linux-imaging-and-printing)
Minimum system requirements	**PC:** Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer.; **Mac:** Apple®OS X El Capitan (v10.11) macOS Sierra (v10.12) macOS High Sierra, (v10.13); 1.5 GB HD; Internet required; USB
Power[5]	**Power supply type:** Internal (built-in) Power Supply; **Power requirements:** 110V - 127V nominal @ +/-10% (min 99V, max 140V), 50 - 60Hz nominal +/- 3Hz (min 47Hz, max 63Hz), **Power consumption:** 307 watts (active printing), 5.3 watts (ready), 0.93 watts (sleep), 0.1 watts (manual off)
Acoustics	**Acoustic power emissions:** 6.5 B(A); **Acoustic pressure emissions:** 51 dB(A)
Operating environment	**Operating temperature range:** 15 to 32.5°C; **Recommended operating temperature:** 17.5 to 25°C; **Storage temperature range:** -20 to 50°C; ; **Operating humidity range:** 10 to 80% RH; **Recommended humidity operating range:** 30 to 70% RH
HP Service and Support options	UC4X4E HP 1y Onsite Exchange NS L 1xxx SVC; UB4Z0E HP 2y Onsite Exchange NS L 1xxx SVC; UB4Z1E HP 3y Onsite Exchange NS L 1xxx SVC; UB4Z2E HP 4y Onsite Exchange NS L 1xxx SVC; UC4X5E HP 5y Onsite Exchange NS L 1xxx SVC; UB4Z3E HP 2y NBD Exchange NS L 1xxx SVC; UB4Z4E HP 3y NBD Exchange NS L 1xxx SVC; UB4Z5E HP 4y NBD Exchange NS L 1xxx SVC; UB4Z6E HP 2y Std Exchange NS L 1xxx SVC; UB4Z7E HP 3y Std Exchange NS L 1xxx SVC; UB4Z8E HP 4y Std Exchange NS L 1xxx SVC; UB4Z9E HP 2y Return to Depot NS L 1xxx SVC; UB5A0E HP 3y Return to Depot NS L 1xxx SVC; UB5A1E HP 4y Return to Depot NS L 1xxx SVC

Learn more at
http://www.hp.com