


TOZO

6.0 Call control



Tap "L" or "R" touch area to answer the call or it will answer the call automatically.
Hold "L" or "R" 2s the sensing area to hang up the call.
Hold "L" or "R" 2s the sensing area to reject the call.

7.0 Charging

7.1 Charging of Charging case

Please remove any protective film before use(if applicable), and fully Charge the earbuds along with the charging case before the first use.

0-20%	Red light
20-80%	Yellow light
80-100%	Green light
Full charged	White charging the red light is always on, and turn to green light when fully charged

7.2 Charging status of earbuds

In charging	White light is always on
Fully charged	The white light is off

Thank you for purchasing the TOZO authentic product.
For more latest products, parts and accessories,
please visit: www.tozostore.com
For any assistance please contact Email: info@tozostore.com

FC RoHS CE RCM CCC WEEE


TOZO

EN

8.0 Specification

Name	TOZO-A3
Transmission distance	10M
Rated power	3mW
Earbuds battery capacity	3.7V/35mAh
Charging box battery capacity	3.7V/400mAh
Playing Time	>6.5 hours
Charging time of the charging case	1.5 hours
Charging port	Type-C
Size of the earbud	32.2*22.8*23.6 mm
Size of the charging box	70.29*36.1*32.1 mm

TOZO
www.tozostore.com



A3 TRUE WIRELESS STEREO

User Manual

TOZO

EN

Thank you for your choice!

Before using the product, please read this manual carefully, it will help you to operate the product better and get superior performance. Please keep this manual for future use.

1.0 Product description



2.0 Earbuds wearing

Gently insert the earpiece into the cochlea obliquely and adjust it to an appropriate angle. When making a call, turn the earbud microphone towards your mouth to make the call clearer.



TOZO

EN

3.0 Operation of earbuds

3.1 Power on/off

Power on:

1. Open the cover of charging case, the earbuds will power on automatically .
2. Tap and hold the earbuds for over 3 seconds.

Power off:

1. Place the earbuds back into the charging case and close the cover.
2. Tap and hold the earbuds over 5 seconds when not playing media.
3. The earbuds will turn off automatically after it is disconnected over 5 minutes.

3.2 Bluetooth pairing and connection

1. In first use, take earbuds out of the charging case and the earbuds will power on and automatically pair with each other. Open the Bluetooth device, search [TOZO-A3] and select the connection.
2. Non first used, the earbuds will auto connect back to the last pairing device when turning on.
3. If auto connect back fail, please select [TOZO-A3] again on "DEVICES" list. If need to connect to other device, please forget/unpair [TOZO-A3] from current device and repeat step1 to connect to the new one.



TOZO

EN

3.3 Reset

If one of the earbuds not work or fail to pair, please reset it:
Put both of earbuds into the charging case, forget/unpair [TOZO-A3] on your device.
1.Open the charging case and keep the earbuds in it.
2.Hold the charging case button for 8 seconds, the indicator light on the box flash 5 times, and the white light on the earbuds fast fast.
3.Take the earbuds out of charging case and connect with device again.



Notes:

1. Pairing mode lasts for a maximum of 5 minutes, during which no pairing is performed and no operation is performed, the earbuds will automatically turn off.
- With the device connected to Bluetooth, turn off the Bluetooth, the white light will flash and the Bluetooth will be disconnected.
- If you want to reconnect, please reconnect according to "Power on" and "Bluetooth connection" operations.
2. If the earbuds beyond the receiving range of the phone, there will be a Bluetooth Connection interruption, if they are back to connection range within 5 minutes, the earbuds and the phone will be automatically reconnected.


TOZO

EN

4.0 Music Operation



5.0 Voice assistant



When using single or both earbuds, triple-tap "L" or "R" earbud to wake up the voice assistant.