

材质: 80克书写纸+双面单黑+打印10页
 红色线框不需要印刷 尺寸: 92x120 mm

92 mm
正
反

120 mm

Operating Instructions



Website:www.jtechdigital.com
 Toll Free:1-888-610-2818[US]
 Email:Support@jtechdigital.com

USER MANUAL

J-Tech Digital® SPDIF/TosLink Digital Optical Audio 1x3 Splitter
 Support 5.1





JTD-ID:42


SAFETY AND NOTICE

Dear customer

Thank you for purchasing J Tech Digital's SPDIF TOSLINK Digital Optical Audio Splitter (JT DSP0103). For best results, please read the instructions in this User Manual carefully before connecting, operating or adjusting this product and retain for future reference.

Our state-of-the-art HD converters, switchers, extenders, matrixes and splitters are designed to deliver the best A/V experience possible - easy to set up and use, reliable, cost efficient and ideal for a wide range of home and business applications.

1. Power Indication
 2. SPDIF/TosLink output port A and B
 3. SPDIF/TosLink output port C
 4. SPDIF/TosLink input port
 5. DC/5V Power Adaptor Interface



3

SPECIFICATIONS: ADSP0103M1

Support audio format.....LPCM2.0/DTS/Dolby-AC3
 Peak wavelength.....650nm
 Max baud rate.....16Mbps
 Output cable distance≤40m(Use the optical fiber cable loss less the 0.2Db/m)
 Max working current.....100mA
 Power adapter format.....Input:AC (50HZ, 60HZ) 100V-240V; Output: DC5V/500mA
 Operating Temperature range.....(0 to +40°C)
 Operating Humidity ra.....5 to 90%RH (No Condensation)
 Dimension (L x W x H).....54x54x23.5 (mm)
 Weight.....1.23oz

INTRODUCTION

This SPDIF/TosLink Digital Optical Audio splitter splits the audio signal from a connected HD source device, allowing users to send the signal to up to three connected audio devices (soundbar, amplifier, audio converter, surround sound system, etc.). The outputted audio signals flawlessly reproduce the sound quality of your connected source device.

This device comes with a 1-year manufacturer's warranty and lifetime technical support. If you have any questions or concerns, please contact our US based customer support team (available Monday through Friday: 9AM – 6PM CST) online at support@jtechdigital.com or by phone at (888) 610-2818.

FEATURES

- Easy to set up, just plug and play
- Distributes the sound from one input device (TV, cable/satellite box, streaming device, gaming console, etc.) to a maximum of three connected sound devices via SPDIF/TosLink fiber optical cables.
- Excellent sound quality; no signal loss or distortion
- Supported audio formats: LPCM2.0/DTS/Dolby-AC3
- Supports signal retiming for synchronization of digital audio signals

1

Package contents:

x1 SPDIF TOSLINK Digital Optical Audio 1x3 Splitter
 x1 User Manual
 x1 5V/1A DC power adapter




Physical Connection Showing Picture:

Figure 1.0



Figure 1.1



2

NOTES

To get the most use out of your splitter, please remember to:

- Follow all instructions in the User Guide.
- This device is intended for indoor use only. Avoid using or storing this device in an environment with excessive humidity, heat, cold, dust, etc. Don't place drinks on or near the device.
- Unplug the device when not in use.
- Do not drop the device or expose to strong vibrations.
- Only use a soft, dry cloth to clean the device; never use water or cleaning solutions

Trouble Shooting Tips

Here are some troubleshooting tips if you experience problems with your splitter:

Problem: Splitter not receiving power.
Solution: Check to make sure the adaptor is properly connected to the device and/or plugged into a functioning AC power source.
Problem: No Sound to Outputted Devices
Solution: Check the connection between the splitter and the outputted device(s) Check the connection between the input device and the splitter Check to make sure all devices are powered on

5

Problem: Loss of signal to outputted devices

Solution:
 Check to ensure the device is properly connected to the splitter
 Connect the device using a different SPDIF/TosLink cable.

www.jtechdigital.com

Product pictures are for reference only.
 Specifications described hereil are subject to change without prior notification.
 All trademarks are the sole property of their respective companies.
 Copyright © J-Techdigital,Inc.All rights reserved.

制作要求:

产品型号	ADSP0103M1光纤1x3说明书
材质	80g书写纸
料号	A.5.MANUAL913
尺寸	92*120mm
颜色	黑白
备注	
制作人和日期	艾森 2020.01.13